

JOINT

Express Mail: EL674752882US

**DIVISIONAL APPLICATION
FOR
UNITED STATES LETTERS PATENT**

TO THE ASSISTANT COMMISSIONER FOR PATENTS:

BE IT KNOWN, that We,

Neil Singer,	Armonk, NY
Mark Tanquary,	Needham, MA
Kenneth Pasch,	Brookline, MA

have invented certain new and useful improvements in **DYNAMIC SYSTEM**

CONTROL METHOD of which the following is a specification:

Dynamic System Control Method

Field of the Invention

The present invention is directed to altering inputs to, and generating feedforward signals for, a dynamic system so as to reduce unwanted vibrations in the system. The invention has particular utility in speeding up computer disk drives by reducing unwanted vibrations which, if unchecked, could lead to disk read/write errors or excessive noise.

Description of the Related Art

Movement in dynamic systems typically results in unwanted vibrations that are both mechanical and acoustic in nature. These vibrations can have a detrimental affect on the operation of such systems. One dynamic system that is particularly sensitive to unwanted vibrations is a computer disk drive.

A computer disk drive includes an actuator arm having a head mounted at a distal end of the arm for reading from, and writing to, tracks on a magnetic disk. This head is moved by the arm from track-to-track on the disk. Vibrations in the system result from this movement. That is, the head and actuator arm vibrate after reaching a nominal final position. Reading and writing cannot take place by the disk drive until these vibrations go below a certain level; otherwise read/write errors occur. These vibrations may also cause noise.

The period during which the disk drive waits for these vibrations to reach an acceptable level (i.e., the settling time) increases the disk drive's seek time. The drive's seek time comprises the time it takes for the drive's head to come to rest at a position where the head can perform a read/write operation on a particular track. The increase in seek time can be especially acute in cases where the track-per-inch density of the magnetic disk is high. That is, because tracks in these disks are relatively close together, even small vibrations in the head can seriously affect the accuracy of the disk drive and/or increase noise in the drive. Since even small vibrations cannot be tolerated, the settling time is further increased, thereby further increasing the drive's seek time.

Conventional attempts at addressing the foregoing problems in both disk drives and dynamic systems in general have fallen short of satisfactory. That is, such attempts are too computationally intensive to be practical, have failed to provide sufficient reduction in vibrations for use in high accuracy positioning equipment such as computer disk drives, produce sub-optimal trajectories, and/or are overly sensitive to system parameter variations.

Other related problems also plague conventional disk drives. For example, in conventional disk drives, two different controllers are used to position the drive's head on a track. A first controller controls the drive's head to reach a predetermined position near to a final position, at which point a second controller takes over. This second controller moves the head into the final position and regulates the head on a track. Switching between these two controllers increases settling time and, as a result, increases seek time. Also, in conventional disk drives, little or no control over vibrations is included in the derivation of these controllers. Consequently, conventional disk drives may not be able to discern important variations during motion transients.

In view of the above, there exists a need for a way to control computer disk drives and, more generally, dynamic systems, which reduces both mechanical and acoustic vibrations to an acceptable level without undue computational effort and without a substantial reduction in movement speed.

Summary of the Invention

The present invention addresses the foregoing needs by providing methods of controlling movement in a dynamic system so as to reduce mechanical and/or acoustic unwanted vibrations in the system. These methods are relatively easy to perform, produce good results, and have few adverse side effects, thereby making them a significant improvement over the prior art.

In one aspect, the invention determines which parameter will cause a dynamic system to saturate. For example, in the case of a computer disk drive, current commands control the system. However, voltage is the fundamental limiting parameter of the system, since voltage supplied by the drive's power

supply limits the amount of current in the system. In this aspect, the fundamental limiting parameter is used to generate a command for the system which reduces vibrations without causing the system to saturate. In the specific case of a disk drive, the fundamental limiting parameter (i.e., voltage) is also used to generate current commands that do not exceed the voltage limitations of the system.

In another aspect of the invention, a disk drive system is modeled using partial fraction expansion equations. The digital form of those equations is as follows:

$$Finalpos = \sum_{i=1}^N V_i A \Delta t$$

$$0 = \sum_{i=1}^N V_i \frac{Ab}{b-a} (e^{-a(T_{end}-T_i+\Delta t)} - e^{-a(T_{end}-T_i)})$$

$$0 = \sum_{i=1}^N V_i \frac{Aa}{a-b} (e^{-b(T_{end}-T_i+\Delta t)} - e^{-b(T_{end}-T_i)}),$$

- where Finalpos is a final position of the system, A is a scaling factor, a and b are inverse time constants, t_{end} is the time at which a move is completed, V_i are voltage inputs to the system, T_i are the times at which V_i are input, and Δt is a time interval at which V_i are input. Using the above equations, system inputs which produce reduced vibrations can be determined. These equations are particularly powerful when used to solve for a system input in terms of its fundamental limiting parameter. Additional constraints may also be included in the above equations in order to provide a more accurate model of the system.

- In still another aspect of the invention, techniques are provided for reducing system vibrations in its various modes. These techniques may be used alone or in conjunction with the concepts set forth above. One such technique comprises incorporating vibration limiting and sensitivity constraints into the partial fraction expansion equation model so as to reduce vibrations to specific levels. Another technique comprises shaping (e.g., convolving or filtering) a

command determined using the partial fraction expansion equation model to produce a desired output. The entire command may be shaped or only selected portions thereof which produce vibrations. Selective shaping is preferred since it reduces seek time relative to shaping the entire command. Another technique involves commanding in current to produce saturation in voltage. By doing this, it is possible to command voltage switches. The times at which the switches occur can then be set to reduce system vibrations. Other techniques are also provided. These include varying transient portions at the beginning, middle and/or end of a move and using Posicast inputs, among others.

10 In still another aspect, the invention determines an input to the system that will result in limited (or reduced) vibrations, and uses that input as a feedforward trajectory for the system. Several approaches are provided for generating the input, including performing an optimization method on the partial fraction expansion equations. In one approach, the problem of generating an input is separated into a rigid mode problem and a flexible mode problem. Specifically, terms associated with the rigid mode of the system are determined from the partial fraction expansion equations, and terms associated with oscillating or flexible modes of the system are determined based on a system analysis. The rigid body terms are solved for an input which drives the system so as to satisfy its rigid body constraints. This input is then shaped using, e.g., an Input Shaper™ designed to compensate for the flexible modes of the system. Using this approach, the computational difficulty of obtaining a solution is reduced relative to the optimization approach, while still providing an adequate reduction in levels of vibrations in relevant modes of the system. Another approach to generating the input involves creating a closed-loop model of the system. An input which results in reduced vibrations may then be generated based on this model. In still another approach, voltage switch times for a bang-bang input that reduces vibrations are determined based on the partial fraction expansion equations. Input Shaping™ may then be applied to that input so as to provide a further reduction in vibrations.

In other aspects of the invention, various position-velocity ("PV") table formulations are provided for reducing system vibrations. In one approach, a trajectory which reduces system vibrations is generated in accordance with one or more of the techniques set forth above, and that trajectory stored in a PV table.

5 The trajectory can then be used to control movement of the system. In another approach, a shaper is provided at the output of a PV table, and its inverse is provided along the system's feedback path. This arrangement reduces system dynamics via the feedforward direction, and restores loop stability in the feedback direction. In still another approach, an N ($N > 2$) dimensional PV table is used to

10 control a system, in which velocity is a function of position and one or more other variables, such as movement distance, resistance, temperature, etc. In yet another PV approach, current commands are shaped at transition(s) (e.g., at deceleration) so as to yield desired levels of vibrations. During non-transitional states, a trajectory in a PV table is followed.

15 While the above-summarized methods significantly enhance the operation of dynamic systems, such as computer disk drives and other data storage devices, it is also preferable to allow end-users some control over the system's operation. For example, a user may want a disk drive that has a relatively low seek time (i.e., a disk drive that is fast), but may not care about

20 acoustics. Similarly, the user may be more focused on acoustics than on seek time. Thus, there exists a need for a way by which an end-user can control operation of a disk drive. In particular, there exists a need for a simple way to control operation of the disk drive, which permits the user to select operational parameters, such as seek time and acoustic levels, in addition to other features.

25 The present invention addresses these needs by providing a GUI and/or mechanical switch(es) through which an end-user may alter operational parameters of a disk drive, including, but not limited to, the drive's seek time, noise level, and power consumption. By providing these features, the invention enables the user to customize operation of a disk drive relatively easily without

30 requiring significant hardware and/or software modifications.

This brief summary has been provided so that the nature of the invention may be understood quickly. A more complete understanding of the invention can be obtained by reference to the following detailed description of the preferred embodiments thereof in connection with the attached drawings.

5

Brief Description of the Drawings

Figure 1 is a perspective view of a computer system through which the present invention may be implemented.

Figure 2 shows the architecture of the computer system.

10 Figure 3 shows process steps for generating a graphical user interface in accordance with the invention.

Figure 4 to 9 show graphical user interfaces that can be generated by the invention.

15 Figure 10A is a cut-away view of a disk drive that is controlled by the present invention.

Figure 10B is a block diagram of circuitry for controlling the disk drive in accordance with the invention.

Figure 11 is a feedback diagram of a computer disk drive.

20 Figure 12 shows a plot of "good" moves versus "bad" moves for different movements made by a computer disk drive.

Figure 13 is a feedback diagram of a prior art disk drive system.

Figure 14 is a feedback diagram of a disk drive system in accordance with the present invention.

25 Figure 15 is a block diagram showing the relationship between an input and an output of a finite impulse response filter shaping technique.

Figure 16 is a block diagram showing the relationship between an input and an output of a finite impulse response filter inverse shaping technique.

Figure 17 is a block diagram showing the relationship between an input and output of a tapped continuous delay line filter shaping technique.

Figure 18 is a block diagram showing the relationship between an input and an output of a tapped continuous delay line filter inverse shaping technique.

Figure 19 is a block diagram showing the relationship between an input and an output of an infinite impulse response filter shaping technique.

5 Figure 20 is a block diagram showing the relationship between an input and an output of an infinite impulse response filter inverse shaping technique.

Figure 21 shows examples of trajectories in a position-velocity table used in embodiments of the present invention.

Figure 22 depicts parameterization of trajectories in a position-velocity
10 table in accordance with the present invention.

Figures 23A and 23B show optimal rigid body voltage commands for 1 and 3000 track moves, respectively, for a disk drive system.

Figure 24 shows a digitized input voltage waveform.

Figure 25 shows the waveform of Figure 24 conceptualized as a series of
15 pulses.

Figure 26 shows each of the pulses of Figure 25 represented as a pair of impulses.

Figure 27 shows a block diagram of a feedback system.

Figure 28 shows application of a Laplace differentiation operator to inputs
20 to the system shown in Figure 27.

Figure 29 shows scaled versions of the inputs of Figure 28.

Figure 30 shows a reduction, using block diagram algebra, of the inputs shown in Figure 29.

Figure 31 shows a reduction of the inputs shown in Figure 30.

25 Figure 32 shows a plot of impulses of a three pulse shaper together with a sine wave representation of undamped vibration.

Figure 33 shows a plot of digital pulse spacing for the three pulse shaper together with a sine wave representation of undamped vibration.

Figure 34 shows pulse spacing for a three pulse shaper and a sine wave
30 representation of vibration.

Figure 35 shows a voltage pulse response of a dynamic system.

Detailed Description

The present invention comprises computer-executable code (i.e., computer-executable process steps) for controlling operation of a disk drive or, more generally, any dynamic system. For the specific case of a disk drive, the invention includes code which generates a GUI, which accepts inputs into that GUI, and which outputs commands to a disk drive causing the disk drive to conform its operation to the GUI inputs. The invention can be used in any type of computer/disk drive system, such as a desktop computer, laptop computer, or the like. For the sake of brevity, however, the invention will be described in the context of a desk-top computer system only.

Figure 1 shows a representative embodiment of a computer system 1 on which the invention may be implemented. As shown in Figure 1, personal computer ("PC") 2 includes network connection 4 for interfacing to a network, such as the Internet, an ATM network, or the like, and fax/modem connection 5 for interfacing with other remote devices such as a digital camera, digital video camera, and the like. PC 2 also includes display screen 6 for displaying information to a user, keyboard 7 for inputting text and user commands, mouse 9 for positioning a cursor on display screen 6 and for inputting user commands, and disk drive 10 for reading from and writing to floppy disks installed therein. PC 2 may also have one or more peripheral devices (not shown) attached thereto for inputting text, graphics, images, or the like, and/or for outputting images.

Figure 2 shows the internal structure of PC 2. As shown in Figure 2, PC 2 includes memory 11, which comprises a computer-readable medium such as a computer hard disk. Memory 11 stores data 12, applications 14, and operating system 15, among other things. In preferred embodiments of the invention, operating system 15 is a windowing operating system, such as Microsoft® Windows98 or Microsoft® Windows NT; although the invention may be used with other operating systems as well. Among the applications stored in memory 11 is computer code to implement the present invention, namely disk drive engine

16. Alternatively, disk drive engine 16 may be stored in a read-only memory ("ROM"), or the like, together with other operational firmware for disk drive 10. In brief, disk drive engine 16 is comprised of computer-executable process steps which, inter alia, generate a GUI for controlling operation of disk drive 10 and
5 output commands to disk drive 10 causing disk drive 10 to conform its operations to settings in the GUI. A more detailed description of disk drive engine 16 is provided below

Also included in PC 2 are display interface 17, keyboard interface 19, mouse interface 20, disk drive interface 21, computer bus 22, RAM 24,
10 processor 25, and printer interface 26. Processor 25 comprises a microprocessor or the like for executing applications, such those noted above, out of RAM 24. Such applications may be stored in memory 11 (as noted above) or, alternatively, on a floppy disk in disk drive 10. Processor 25 accesses applications (or other data) stored on a floppy disk via disk drive interface 21.

15 Application execution and other tasks of PC 2 may be initiated using keyboard 7 or mouse 9, commands from which are transmitted to processor 25 via keyboard interface 19 and mouse interface 20, respectively. Similarly, application execution may be initiated remotely via, e.g., network interface 4 and a network interface card (not shown). Output results from applications running
20 on PC 2 may be processed by display interface 17 and then output via network interface 4 or, alternatively, displayed to a user on display 6. To this end, display interface 17 preferably comprises a display processor for forming video images based on video data provided by processor 25 over computer bus 22, and for outputting those images to display 6. Output results from other applications
25 running on PC 2 may be provided to an attached printer via printer interface 26.

Turning to disk drive engine 16, this application comprises computer code to control operation of disk drive 10 either according to one of a plurality of well-known conventional methods or according to one or more of the proprietary methods described herein. Disk drive engine 16 further includes code
30 for generating a GUI for interactively controlling at least one of a seek time, a

noise level, and a power consumption of a disk drive. The GUI includes a controller that is operated by a user so as to alter settings in the GUI for one or more of these parameters. Thereafter, disk drive engine 16 generates and outputs commands to the disk drive causing it to conform its operation in accordance with the altered settings in the GUI.

1.0 User Interface

Figure 3 is a flow chart for controlling operation of a disk drive using disk drive engine 16. To begin, step S301 generates a GUI and displays that GUI to the user via display 6. Figure 4 shows such a GUI, labeled 27. GUI 27 includes a window 70 for selecting a disk drive to be controlled. That is, although the computer system shown in Figure 1 includes only one disk drive, many systems include more than one disk drive. Window 70 provides a way for a user to select which disk drive to control. Figure 9 is a close-up view of window 70. A disk drive can be selected simply by pointing and clicking on that drive in window 70. The selected drive is then highlighted, as shown.

As shown in Figure 4, GUI 27 also includes controller 29. Controller 29 is used to alter a seek time and a noise level of disk drive 10. In this particular embodiment, controller 29 comprises a sliding bar 30 which moves along a continuum 31 between a relatively high noise level/low seek time (“Quick”) end 32 and a relatively low noise level/high seek time (“Quiet”) end 34. Disk drive noise level and seek time vary inversely along the continuum, meaning that, as the noise level of the disk drive progressively increases, the seek time of the disk drive progressively decreases. Likewise, as the noise level of the disk drive progressively decreases, the seek time of the disk drive progressively increases. By moving sliding bar 30, it is possible to vary both the seek time and noise level parameters simultaneously.

In the preferred embodiment of the invention, sliding bar 30 moves between discrete positions on continuum 31, meaning, e.g., between a first position corresponding to high noise level/low seek time (“Quick”) end 32, a

second position corresponding to a mid-point between the two ends on continuum 31, and a third position corresponding to low noise level/high seek time (“Quiet”) end 34. Alternatively, there may be more than three discrete levels or noise and seek time may vary continuously between the two ends of continuum 31.

5 The level of noise in a disk drive is due to vibrations at particular frequencies, such as 6.6 KHz, 6.0 KHz, 5.0 KHz, 4.2 KHz, and 1.3 KHz. On the other hand, mechanical vibrations, which reduce seek time, result from vibrations at different frequencies, such as 3.3 KHz. By moving the sliding bar of controller 29 along the continuum, an end-user is effectively determining which of the
10 above frequencies should be reduced and/or how much the reduction should be. For example, in a case that Input Shaping™ (described below) is used to reduce vibrations, by moving sliding bar 30, the user effectively selects one or more shaping functions for reducing vibrations at specific frequencies, and causes disk drive engine 16 to convolve those functions with the appropriate disk drive inputs
15 in order to implement the desired vibration reduction.

 In GUI 27 the noise level and seek time vary inversely along continuum 31 such that there is an effective trade-off between seek time and noise level, meaning that as seek time increases, noise level decreases and vice versa. These variations are not necessarily linear; although they may be. As an alternative to
20 sliding bar 30, the GUI may include boxes into which discrete noise levels and/or seek times are entered. For example, as shown in Figure 5, the GUI may include entry box 37 into which a noise level value is entered and display box 39 which displays a corresponding numerical value of the seek time. In this case, the GUI preferably also includes up/down arrows 41 which are used for selecting the
25 various noise level values. On the other hand, these values may be input directly via mouse 9 and keyboard 7. As another alternative, the seek time may be settable via entry box 37 and the corresponding noise level displayed via display box 39. In either case, the numerical value displayed in the display box is calculated by disk drive engine 16 based on the value set in the entry box.

Returning to Figure 4, GUI 27 may also include a second controller, such as check box 42. This controller causes the disk drive to enter a power-saving mode. The power-saving mode comprises a state during which the disk drive reduces its power consumption by a predetermined amount. The power-saving mode may be set in conjunction with varying the seek time and the noise level. That is, in the power saving mode, the set seek time and noise level are achieved using less power than would otherwise be required. This is achieved, e.g., by convolving one or more predetermined functions with a command input to a voice coil motor in the disk drive.

On the other hand, a reduction in power consumption may be achieved via a controller, such as controller 44 shown in Figure 6. Controller 44 comprises a sliding bar 45 which moves along a continuum 46 between a relatively high power consumption/low seek time end 47 and a relatively low power consumption/high seek time end 49. As was the case above, sliding bar 45 may move between discrete values along the continuum. Thus, in this embodiment, disk drive power consumption and seek time vary inversely along the continuum, meaning that, as the power consumption of the disk drive progressively increases, the seek time of the disk drive progressively decreases. Likewise, as the power consumption of the disk drive progressively decreases, the seek time of the disk drive progressively increases.

By moving sliding bar 45 it is possible to vary both seek time and power consumption simultaneously. For example, varying power consumption may be achieved by convolving one or more predetermined functions with a command input to a voice coil motor in the disk drive. Selection of the predetermined functions is performed based on the settings of the sliding bar. Of course, the functions may be set in other ways as well (as is the case throughout this application). For example, the functions may be selected from predetermined trajectories in a position-velocity ("PV") table, as described herein below.

Figure 7 shows yet another alternative configuration for the GUI. As shown in Figure 7, the GUI could include separate controllers 50 and 52 for

reducing both power consumption and noise level, respectively, as a function of seek time. Thus, (i) as noise level increases, seek time decreases, and vice versa, and (ii) as power consumption increases, seek time decreases, and vice versa. The sliding bars shown in Figure 7 preferably have all the characteristics of that shown in Figure 4. As shown in Figure 8, numerical values for noise level and power consumption may be implemented, as in Figure 5. Here, a numerical value is calculated for seek time as well based on the noise level and power consumption settings, and displayed in the GUI as shown.

Returning to Figure 4, GUI 27 may also include a preview controller, shown at 54, to cause the disk drive to operate using parameter(s) set by controller 29. This preview controller may comprise a button or the like, which a user can click on, and which causes the disk drive to operate in a "preview" mode. The preview mode may cause the disk drive to seek between various tracks on a disk so that the user can experience the noise level and seek time settings in the GUI. If these levels are unacceptable, the user may then revise the GUI inputs, and preview the drive's operation based on such newly-set inputs. This process can be repeated as often as desired until the user achieves the desired settings. Preview mode may also be pre-set to execute automatically each time the GUI settings are altered.

GUI 27 may also include one or more display areas 55, as shown in Figure 4. These display areas may provide a numerical indication of the noise level of the disk drive, its seek time, and/or its power consumption rate. Display areas such as these are generally most beneficial in cases where parameters are set using a sliding bar, as is the case, for example, in Figures 4, 6 and 7. Likewise, a display area may be provided which informs the user of the amount of hours that a computer (e.g., a laptop) can operate with an existing power supply. To determine this value, disk drive engine 16 monitors the computer's power supply directly, or estimates the amount of power left based on the total time the computer has been running with the present supply, as well as other relevant parameters.

Returning to Figure 3, following step S301, in which a GUI is displayed, processing proceeds to step S302. In step S302, the user inputs desired settings into the GUI. These settings, of course, will depend upon the available options in the GUI, examples of which are described above. For instance, the user may
5 input some combination of a new seek time, power consumption rate, noise level, etc. Step S302 may be performed locally or remotely via network interface 4. That is, the GUI may be displayed on a remote networked PC, and the settings therefor applied to the local PC. In any event, once the new parameter setting are input in step S302, they may be confirmed via "OK" button 60, canceled via
10 "Cancel" button 61, or applied to the disk drive via "Apply" button 62. The difference between "OK" button 60 and "Apply" button 62 is that "OK" button 60 merely stores the new settings in memory (e.g., memory 11), whereas "Apply" button 62 applies the settings to the disk drive, overriding any previous hardware or software settings.

15 Next, in step S303, commands (e.g., electrical signals) are generated for controlling disk drive 10 in accordance with the settings set in the GUI. Exactly how these commands are generated may vary, depending upon the way in which the disk drive is controlled. Assuming, for illustration's sake, that the disk drive is being controlled via Input Shaping™, step S303 comprises
20 involving various inputs to the disk drive with predetermined functions which are selected based on settings in the GUI in order to produce disk drive inputs that achieve the results specified in the GUI. These functions may be stored, e.g., in memory 11 or in another memory on the system. Sections 2 to 11 below describe a variety of methods that may be used to control operation of the disk drive, any
25 of which may be used in step S303 based on the GUI setting and other factors.

Once the necessary commands have been generated, processing proceeds to step S304, wherein these commands are provided to control operation of the disk drive. Thereafter, a user may again alter the drive's operation simply by calling up a GUI using, e.g., mouse 7, and entering desired operational
30 parameters. Following step S304, processing ends.

At this point, it is noted that the GUI is not limited to the combinations of features shown in the figures. That is, a GUI may be generated in step S301 with includes any one or more of the foregoing features, subject to certain constraints inherent in the system. Likewise, additional features not described herein, but which are well known to those skilled in the art, may also be included in the GUI. As an alternative to the GUI, or to supplement the GUI, the disk drive may include one or more electro-mechanical manual switches for controlling all or part of the drive's operation in the manner set forth above. For the purposes of the present invention, a "jumper" is considered to be within the definition of electro-mechanical manual switch.

2.0 System Control

The following control methods are preferably implemented via computer-executable process steps in disk drive engine 16 so as to effect high-speed moves in a disk drive, such as drive 10. However, it is noted that these methods are not limited to use with disk drives. Rather, the methods described herein can be used to control any type of dynamic system which moves from one state to another state. In fact, any unwanted dynamic behavior that can be quantified in a mathematical expression can be reduced by the present invention. For example, using the present invention, a disk drive in a Redundant Array of Independent Drives ("RAID") can be commanded to move in less time than has heretofore been possible without substantially exciting neighboring drives and while simultaneously reducing acoustic vibrations that result in noise. The designer simply need select which vibrations or dynamic behavior is troublesome, identify constraints and, using the technology presented herein, choose from among several approaches for generating optimal or near optimal moves that reduce those vibrations or dynamic behavior. As used herein, the term "vibrations" can refer to mechanical and/or acoustic vibrations that cause noise.

Figures 10A and 10B show close-up views of disk drive 10. As shown, disk drive 10 includes voice coil motor 72 having a rotor (not shown),

actuator arm 74, sensor 75, and head 76. These components are controlled via disk drive engine 16, or portions thereof, running on a controller/processor 73. This processor may comprise processor 25 set forth above or, alternatively, a separate controller dedicated to the disk drive which receives commands from processor 25. Head 76 reads to, and writes from, tracks (not shown) on magnetic disk 77 installed in drive 10. Actuator arm 74, on which head 76 is mounted, controls the motion of head 76 between the tracks on magnetic disk 77. Motor 72 drives actuator arm 74 in accordance with control signals received from processor 73. These control signals are generated based, at least in part, on a desired position of head 76 and an actual measured position of head 76 provided via signal 79. Movement of head 76 from an initial position to the desired position occurs within the device's seek time. The seek time for disk drive 10 comprises the time it takes for head 76 to move from an initial position to rest at a position where head 76 can perform a read/write operation on a particular track of magnetic disk 77.

The seek time for computer disk drive 10 can be reduced by commanding a component in disk drive 10, such as head 76, to move from one location to another while satisfying constraints on mechanical vibrations, acoustic vibrations, drive mounting vibrations, or any combination of constraints, physical limitations, and/or parameter variations. Several different methods for reducing such vibrations are described below in detail. One such technique involves altering system inputs that are specified as a function of time. Another technique involves generating a position-versus-velocity (hereinafter "PV" or "position-velocity") table using dynamic elements, e.g., constraints or the like, so as to produce PV table trajectories which result in reduced vibrations. In this regard, the terms "input" and "trajectory" may refer to either a reference command for a controller to follow or a feedforward signal within the controller. Still another technique involves modifying the current industry-standard PV table so that an improved PV table is constructed and used. Several methods for generating PV tables are also provided, together with ways to use an Input Shaper™ in

combination with a PV table in order to reduce unwanted vibrations. Also presented are several modifications to the foregoing embodiments which have differing levels of optimality and ease of implementation.

Processor 73 determines which of these techniques to apply based on a variety of factors, such as user inputs to the GUI and the identity of the disk drive. For example, time can be traded off against amount of vibration reduction and robustness to parameter variation. In a given application, the amount of vibration reduction required to make end-of-move conditions acceptable can be a function of the movement distance or other parameter. When this is the case, it is advantageous to trade-off shaping time against shaper effectiveness (meaning amount of vibration reduction) such that (i) vibrations, both mechanical and acoustic, are reduced to an acceptable level (not excessively attenuated), and (ii) shaping time is less than it would be if the vibration were excessively attenuated. When more vibration reduction is required, a longer shaper can be used; when less vibration reduction is required a shorter shaper can be used; and when no vibration reduction is required, then no shaper (zero length) can be used. In this example, shaper selection was from among a discrete collection of shapers. It is also possible to use a single adjustable shaper, e.g. one in which the time interval between pulses is shortened; resulting in a desired shorter shaping time and reduced vibration reduction.

3.0 Fundamental Limiting Parameter

One of the techniques utilized by the present invention is a method for commanding systems that saturate in an optimal manner while still reducing unwanted dynamics. Since all systems saturate in some manner, a method for setting up a command profiling approach is presented herein which first determines a fundamental limiting parameter for the system, second applies either a command shaping or whole-trajectory-generating technique to that parameter, and third schedules the shaped command to be output to the system.

The fundamental limiting parameter of a system is the parameter that causes the system to saturate. In the case of a computer disk drive, current commands control the system. However, the fundamental limiting parameter is voltage, since voltage supplied by the drive's power supply limits the amount of current in the system. By identifying the fundamental limiting parameter of a system in this manner, and processing that parameter in accordance with the techniques provided herein, it is possible to provide for greater control over system movement than has heretofore been possible.

In this regard, there are several disadvantages to not using the fundamental limiting parameter for command profiling. First, there is no a priori way to generate a command signal that does not saturate the system. If the system is allowed to saturate a signal at any time after any command profiling technique is applied, the vibration (or unwanted dynamics) reduction benefit of command profiling will be degraded. The amount of degradation depends on how much the signal is saturated. Therefore, sub-optimal trajectories often result. As examples, optimal rigid body voltage commands for a disk drive system for 1 and 3000 track moves are shown in Figures 23A and 23B, respectively (see section 6.3 below for a discussion of rigid vs. flexible system modes). The optimal current command that corresponds to this voltage is highly complex because it depends on the state of the system (in this case, velocity, due to the back EMF of the drive's motor). Any simple current command would necessarily be sub-optimal if the designer is to guarantee that the system is not to saturate. Section 3.1 below describes how this is achieved.

For optimal moves, the system should be commanded with inputs that take the system to saturation limits without exceeding these limits. The second disadvantage of not choosing the fundamental limiting parameter is that these saturation limits cannot be determined without including the entire system dynamics. Therefore, the solution to the problem is significantly more complex. Additionally, once vibrational constraints are included in the problem, the solution increases yet again in complexity. Once the proper selection of a

fundamental limiting parameter is made, an input that approaches saturation without unknowingly trying to exceed the limit can be generated.

Another approach to handling the presence of nonlinearities, such as saturation, along the feedforward path is to place a shaping module after the nonlinear element. For example, if a signal can saturate along the feedforward path, the signal should be saturated before the shaping operation. In the case of a digital-to-analog conversion ("DAC") saturation, the output of the feedforward calculations might need to be limited to plus or minus 16,000 counts. If a shaping technique is to maintain the vibration reducing benefits, the output should be limited to 16,000 counts and then shaped.

Still another approach to handling saturation of a parameter, while maintaining the vibration reduction benefits of the various techniques presented herein, is to pre-saturate a signal. One condition under which this would be necessary is if the saturating element is outside of the control of the designer (e.g., the saturation occurs in a hardware amplifier). In this case, it is impractical to perform shaping after saturation. Under this condition, the signal should be pre-saturated and then shaped. Pre-saturation involves determining a mathematical expression for the condition under which the system will saturate during a move, and saturating the signal before it is shaped.

This approach of placing the shaping operation after any nonlinear block is applicable to the technique of putting Input ShapersTM and Inverse ShapersTM in a loop, as presented in section 9 below. All of the same rules apply in that any saturation or nonlinear operation must occur outside the path between the ShaperTM and Inverse ShaperTM. If the loop is cut open and all of the dynamic elements between the ShaperTM and Inverse ShaperTM are extracted, the dynamic elements must all be linear (or nearly linear); otherwise the effect of unwanted dynamic reduction is degraded. Additionally, the pre-saturation technique can be used in situations in which saturating elements must necessarily be between the ShaperTM and Inverse ShaperTM.

3.1 Using The Fundamental Limiting Parameter While Generating Feedforward Signals In A Different Parameter

In a disk drive, current is usually commanded to a transconductance amplifier. The fundamental limiting parameter for a disk drive is voltage. It is, however, possible to generate current commands that maintain a limit in voltage. This section explains how to generate such commands.

The first method for generating a current command that does not exceed the voltage limitations of the system is to solve a set of equations directly for the command input which, in this case, is the feedforward signal to the transconductance amplifier. The following equation is used to generate an input that takes the system to zero final velocity:

$$\sum_{i=1}^N A_i = 0,$$

where the A's comprise the amplitudes of the current commands at time interval i, and N comprises the last time interval. The following equation determines the velocity, v, at each time interval i

$$v_i = C_{vscale} \sum_{j=1}^{i-1} A_j,$$

where A comprises the current inputs and C_{vscale} comprises a disk-drive-dependent constant. The final desired position/state of the system, P_{final} , is determined as follows

$$P_{final} = \sum_{j=1}^N v_j.$$

The voltage limit constraint, V_{lim} , comprises the maximum voltage that is being commanded (usually the drive supply voltage). For a disk drive, this is usually on the order of 12V. V_{lim} limits the A value by the following equation:

$$-V_{lim} < \sum_{i=1}^J A_{j-i+1} R_i < V_{lim}, \quad j = 1 \rightarrow N,$$

5 where R_i is the pulse response of the amplifier and drive system to the voltage command. The voltage pulse response may be determined by outputting a unit pulse to the amplifier connected to the disk drive and measuring the voltage response of the amplifier. The values of R_i are chosen by means of a multiple step process outlined below.

10 In this regard, Figure 35 shows a voltage pulse response from a computer simulation. The smooth curve is the continuous voltage response. The “square step” curve represent the system’s digital sampling rate (or output rate, see section 7.1 below), DT. The first peak occurs T_{peak} after the initial pulse is issued to the system. The first value of R is determined by measuring this peak value and setting the first R equal to this peak value. All subsequent values of R are determined by sampling in DT intervals after this initial peak. The step curve in the figure shows the actual values for this particular example. In this case, a complex voltage curve is reduced to a relatively small number of sample points to be used in one of the several solution techniques described herein.

20 Alternatively, the pulse response R can be computed as a calibration step in the disk drive or generated at design time. All of the required information for generating an optimal current command is included in this pulse response (except for slew rate limits discussed below). The amplifier is reasonably linear, therefore, saturation of the amplifier is easily predicted from the pulse response. Also, the pulse response may be altered as a function of a measured or estimated parameter change.

25

The effect of the back EMF of the drive's voice coil motor on the above calculation may be notable. If the voltage pulse response R is calculated analytically (or from a model), the voltage is constant and non-zero at steady state because the system reaches a finite velocity from a pulse in acceleration. In Figure 35, the pulse response achieves a small positive value (which cannot be seen on the plotted resolution). Experimentally, friction and flex circuit spring effects eliminate this constant velocity and cause the drive's head to stop moving. In this case, a constant term in consistent units equal to $K_{BEMF}C_{VSCALE}$ should be added to the voltage pulse response R so that it includes the effect of back EMF and allows for a more aggressive command.

An example computer code written in GAMS that may be used to solve equations 1 to 4 above for values of A is provided below in Appendix B. By solving the set of equations in Appendix B, a time optimal, unshaped current command can be generated. This set of equations can be solved in many different ways. For example, the entire set can be solved as a constrained optimization in which the goal is to generate the minimum time solution. This may also be performed without optimization by solving for a feasible solution (the first step of a Simplex solution, for example) and then reducing the length, N , of the solution vector until no answer can be found (a binary search may be used here). Another method is to determine a function that predicts the length of the solution and then, without any iteration, find a feasible solution. One such prediction function comprises the switch time equations set forth in Appendix A, described below. Another approach is to fit a curves to such a solution. In this case, an exact answer is not needed so long as the curve prediction functions overestimate the solution lengths and never underestimate the solution lengths.

It is also possible to solve for an optimal, unshaped command in real-time which is not in the system's fundamental limiting parameter. For example, we can solve for current (A) by setting a final value of the fundamental limiting parameter, here voltage (V), as follows (of course, the invention is not limited to use with current and voltage, any parameters can be used). This

approach is based on the fact that the maximum current command output value is related to previous output values by the following relationship:

$$A(i) = \frac{V_{\max} - \sum_{j=2}^i A(i+1-j) R(j)}{R(1)},$$

where R is the voltage pulse response and V_{\max} is the maximum voltage V_{\lim} on acceleration (or any condition under which $A_{i+1} > A_i$) and $-V_{\lim}$ on deceleration (or any condition under which $A_{i+1} < A_i$). Equation 5 assumes that the back EMF of the drive's voice coil motor is already included in $R(j)$. The back EMF term may be added to $R(j)$ as set forth above, if needed. Equation 5 can be further simplified since the $R(j)$ values become insignificant after only a few samples. Consequently, an efficient approximation would only use a few samples of the $R(j)$ series. If samples are dropped for an efficient approximation, the back EMF of the drive's voice coil motor times the number of dropped samples may be added to equation 5 to achieve an even more accurate result if that value is deemed significant.

A rigid body current command can be generated from equation 5 in a step-by-step fashion, where each response depends only on previous values. First the system is accelerated. Each current step is computed from equation 5. Next, the system is decelerated. This deceleration may be to zero for a constant velocity coast in the middle of the move or it may be a transition to negative deceleration and then to a stop. Deceleration is computed from equation 5 by reversing the sign of V_{\max} . Under coast conditions, a second deceleration phase will be started (again using equation 5 with a negative value for V_{\max}). Lastly, when deceleration is complete, the transition back to zero current is governed by equation 5 with a positive value, once again, for V_{\max} .

The only unknowns in the previous equations are the times at which to transition between regions. There are several ways to solve these problems.

Shaped™ switch times derived in section 6.9 below may be used as reasonable estimates for the transition times; although any curve fit or lookup table would also suffice. This lookup is especially useful given that on many disk drives, one current profile is often currently used and scaled for a range of seek distances.

- 5 Additionally, using this approach the final position will not be exact and a zero velocity must be guaranteed. The problem of zero velocity means that an additional constraint must be used in computing the final values. Equation 5 defines the *limit* on the current value; therefore, in deceleration, for example, any value more negative than that value may be used without exceeding the limit. As
- 10 a result, the final values can be chosen so that the sum of the current values equals zero (no residual velocity). The distance traveled will be incorrect (but very close). The last step is to scale the waveform linearly by the percentage error so that the final value is correct. This operation can even be performed as part of the next step, which is the shaping operation. The shaper can be scaled and then
- 15 convolved with the rigid body current command. Another option is to increase the value of N, thus adding extra points, and directly solving for the extra A(i) values such that velocity equals zero and position equals "final position".

- There are many variations to the above approach which may yield fewer computations. Also any vibration suppression technology can be subsequently
- 20 applied to the rigid body current command. Furthermore, V_{\max} may be changed as the calculation progresses to optimize scaling. For example, with the knowledge that the current command is to be shaped (and thereby reduced in magnitude) a more aggressive value (higher V_{\max}) can be computed.

- Physical amplifiers have finite limits on the rate at which the voltage can
- 25 change. The pulse response calculated above does not include such limits. It should be noted that a constraint on the rate of change of voltage in the current amplifier can be added to the equation set during numerical solution in the same manner as all of the other constraints. The slew rate becomes important when rapid transients of the input are allowed. The slew rate equation is simple. For
- 30 example, an amplifier chip may limit at 1.25 volts per msec. The voltage

constraint used in calculating the input is the minimum of either the voltage generated from the Voltage Limit Constraint above or $(old_voltage + (A(I) - A(I-1)) * Volt_Rate_Limit)$ with the correct unit conversions.

5 3.2 Rescaling of Current Inputs

The current commands generated in the previous section are completely scaleable. If for example, a 5 track seek has been created by generating an optimal current command and subsequently shaping it, a 4 track, shaped move can be made by simply rescaling the input by 4/5. The move time
10 will be the same as that of a 4 track seek, however, the computation is simple. The point is that shaped moves can be scaled in amplitude and they will continue to reduce vibrations and acoustic noise.

4.0 Partial Fraction Expansion Equation System Model

15 Once a parameter in the system, such as the fundamental limiting parameter, has been identified, an input to the system in terms of that parameter can be generated. In order to generate an input which results in reduced system vibrations, it is first necessary to generate a set of simple equations that define the system. The first step in generating such system equations is to write the transfer
20 function for a simple model of the system.

Figure 11 shows a third order model for a disk drive system such as that shown in Figures 10A and 10B. For system 80 shown in Figure 11, a voltage V is input so as to control movement of head 9 to a particular track on a recording medium. To this end, blocks in system 80 convert voltage V into a
25 current i, convert current i into torque J, convert torque J into frequency T, convert frequency T into velocity v, convert velocity v from meters-per-second into tracks-per-second, and convert tracks-per-second into a location of a particular track on a recording medium such as a magnetic disk.

To generate a set of equations for system 80, the transfer function $H(s)$ therefor must first be determined. The transfer function $H(s)$ for system 80 is as follows:

$$H(s) = \frac{K_t l k}{(I_e s^2 J_m + (I_e R_m + R_e J_m)s + R_e R_m + K_t K_b) s},$$

- 5 where K_t is the motor torque constant, K_b is the back EMF constant, l is the actuator arm radius, k corresponds to track density on a recording medium, I_e is the inductance of a voice coil in the motor, J_m relates to inertia of the motor's rotor, R_m corresponds to an amount of viscous friction in the motor, and R_e corresponds to an amount of electrical resistance in the system.

- 10 Next, $H(s)$ is written as an equivalent transfer function in terms of three parameters, namely A , a and b , as follows:

$$H_{eq}(s) = \frac{Aab}{s(s+a)(s+b)},$$

where A corresponds to a scale factor and a and b correspond to inverse time constants. Specifically, in terms of the parameters in equation 6, A is defined as follows:

$$A = \frac{K_t l k}{R_e R_m + K_t K_b}.$$

- 15 Variables a and b correspond to two solutions in s , namely s_1 and s_2 , to the

$$I_e J_m s^2 + (I_e R_m + R_e J_m) s + R_e R_m + K_t K_b = 0.$$

following quadratic characteristic equation from equation 6:

After writing $H(s)$ in terms of the equivalent transfer function $H_{eq}(s)$, a modal analysis or a partial fraction expansion is then performed on $H_{eq}(s)$ so that each pole of the system is in a separate term. A partial fraction expansion for $H_{eq}(s)$ is follows:

$$H_{eq}(s) = \frac{A}{s} + \frac{Ab}{(-b+a)(s+a)} + \frac{Aa}{(-a+b)(s+b)}.$$

- 5 Each term of the expression for $H_{eq}(s)$ in equation 10 can then be written as follows:

$$\begin{aligned} F_1(s) &= \frac{A}{s} \\ F_2(s) &= \frac{Ab}{(-b+a)(s+a)} \\ F_3(s) &= \frac{Aa}{(-a+b)(s+b)}. \end{aligned}$$

From equations 11, a time domain response of each term to a unit step (e.g., to a unit voltage) input can be determined. This time domain response is as follows:

$$\begin{aligned} F_1(t) &= At \\ F_2(t) &= \frac{Ab}{a(-b+a)} - \frac{Ab}{e^{at}a(-b+a)} \\ &= \frac{Ab}{a(-b+a)} * (1 - e^{-at}) \\ F_3(t) &= -\frac{Aa}{b(-b+a)} + \frac{Aa}{e^{bt}b(-b+a)} \\ &= \frac{Aa}{b(-a+b)} * (1 - e^{-bt}). \end{aligned}$$

System response to a unit impulse can also be obtained by differentiating the above “step response” equations with respect to time.

To solve equations 12 for a system input, values must be determined for $F_1(t)$, $F_2(t)$ and $F_3(t)$. Examination of the expressions for $F_1(t)$, $F_2(t)$ and $F_3(t)$ reveals that the expressions for $F_2(t)$ and $F_3(t)$ vanish as “t” approaches infinity in a case that the input to the system is zero, which is the case at the end time of a move (hereinafter referred to as time “ t_{end} ”). Since the input is zero at time t_{end} , responses of $F_2(t)$ and $F_3(t)$ decay after time t_{end} . Accordingly, in order to solve for a system input that will move the system to the correct location in a rest state, $F_2(t)$ and $F_3(t)$ should be set to zero at time t_{end} . Furthermore, since the input is zero after time t_{end} , the value of $F_1(t)$ stops changing at time t_{end} . The above two conditions are equivalent to zero velocity and zero acceleration (or current) at the end of the move.

Thus, in the equations for $F_1(t)$, $F_2(t)$ and $F_3(t)$, in a case of zero velocity and acceleration at the end of a move, only the term involving $F_1(t)$ contributes to the final position. An expression can then be written including the response of each mode, namely $F_1(t)$, $F_2(t)$ and $F_3(t)$, at a time corresponding to an end of the move, namely t_{end} , for a voltage V_0 input at t_0 and having transitions at t_1 and t_2 . To this end, $XF_1(t_{end})$ set forth below defines the contribution of $F_1(t)$ to the position at time t_{end} , $XF_2(t_{end})$ set forth below defines the contribution of $F_2(t)$ to the position at time t_{end} , and $XF_3(t_{end})$ set forth below defines the contribution of $F_3(t)$ to the position at time t_{en}

$$\begin{aligned} XF_1(t_{end}) &= V_0 F_1(t_{end} - t_0) - 2V_0 F_1(t_{end} - t_1) + 2V_0 F_1(t_{end} - t_2) \\ XF_2(t_{end}) &= V_0 F_2(t_{end} - t_0) - 2V_0 F_2(t_{end} - t_1) + 2V_0 F_1(t_{end} - t_2) \\ XF_3(t_{end}) &= V_0 F_3(t_{end} - t_0) - 2V_0 F_2(t_{end} - t_1) + 2V_0 F_1(t_{end} - t_2). \end{aligned}$$

Thus, the total movement distance at time t_{end} is expressed as

$$XF_1(t_{end}) + XF_2(t_{end}) + XF_3(t_{end}) .$$

As noted above, the expressions for $F_2(t)$ and $F_3(t)$ vanish as “t” approaches infinity in a case that the input is zero, i.e., at the end of a move. Thus, in equations 13, only the term involving $F_1(t)$ contributes to the final position as time approaches infinity. This results in the following three constraint equations that must be satisfied in order for a third order system to reach its desired final position in substantially minimal time, with substantially zero velocity and acceleration

$$\begin{aligned} XF_1(t_{end}) &= Finalpos \\ XF_2(t_{end}) &= 0 \\ XF_3(t_{end}) &= 0 , \end{aligned}$$

where Finalpos denotes the end (or “final”) position of the system. These equations correspond to rigid mode motion constraints since they achieve a final position in the third order model with substantially zero velocity and acceleration.

A digital model of the response of a disk drive system to a unit impulse may be derived based on the foregoing. Figure 24 shows a digital voltage input waveform. The waveform of Figure 24 can be conceptualized as a series of pulses as shown in Figure 25. Each of these pulses can be represented as a pair of impulses, as shown in Figure 26. A first digital constraint is formed by realizing that the system’s final position, Finalpos, is proportional to the area enclosed by the voltage waveform, i.e., the integral of the voltage waveform. The area of the voltage waveform can be determined by inspection of the waveform shown in Figure 24. Specifically, the area is determined as follows

$$Finalpos = \sum_{i=1}^N V_i A \Delta t ,$$

where “ V_i ” corresponds to an area of a pulse “ i ”. Negative values of V_i subtract from the overall sum.

The remaining two digital constraints can be formed using the impulse summation form of the voltage waveform shown in Figure 26.

- 5 Specifically, as noted above, the impulse response of the system can be determined by taking the derivatives of step response equations. For $F_2(t)$ and $F_3(t)$ above, the impulse response equations are as follows:

$$\begin{aligned}\frac{d}{dt}(F_2(t)) &= \frac{Ab}{b-a} e^{-at} \\ &= F_2' \\ \frac{d}{dt}(F_3(t)) &= \frac{Aa}{a-b} e^{-bt} \\ &= F_3' .\end{aligned}$$

- 10 In accordance with constraint equations 12, the response of the series of impulses of the voltage summation form of the voltage waveform, evaluated at time t_{end} , is set to zero in order to form the second and third digital constraints, as follows:

Thus, partial fraction expansion equations corresponding to a digital model of the response of a disk drive system to a unit impulse comprise:

15

$$\begin{aligned}
0 &= \sum_{i=1}^N V_i (F_{2'} (T_{end} - T_i + \Delta t) - F_{2'} (T_{end} - T_i)) \\
&= \sum_{i=1}^N V_i \frac{Ab}{b-a} (e^{-a(T_{end}-T_i+\Delta t)} - e^{-a(T_{end}-T_i)}) \\
0 &= \sum_{i=1}^N V_i (F_{3'} (T_{end} - T_i + \Delta t) - F_{3'} (T_{end} - T_i)) \\
&= \sum_{i=1}^N V_i \frac{Aa}{a-b} (e^{-b(T_{end}-T_i+\Delta t)} - e^{-b(T_{end}-T_i)}).
\end{aligned}$$

Thus, partial fraction expansion equations corresponding to a digital model of the response of a disk drive system to a unit impulse comprise:

$$\begin{aligned}
Finalpos &= \sum_{i=1}^N V_i A \Delta t \\
0 &= \sum_{i=1}^N V_i \frac{Ab}{b-a} (e^{-a(T_{end}-T_i+\Delta t)} - e^{-a(T_{end}-T_i)}) \\
0 &= \sum_{i=1}^N V_i \frac{Aa}{a-b} (e^{-b(T_{end}-T_i+\Delta t)} - e^{-b(T_{end}-T_i)}),
\end{aligned}$$

- 5 where Finalpos, A, a, b and t_{end} are as previously defined, V_i are voltage inputs to the system, T_i are the times at which V_i are input, and Δt is a time interval at which V_i are input.

Equations 19 can be used to solve for system inputs V_i which result in substantially zero velocity and acceleration at the end of a move. These equations can be solved in a number of ways. For example, the equations can be solved using a linear programming method, either on their own or in conjunction with a variety of other constraints. Examples of such constraints include vibration constraints and physical constraints such as power consumption or heat buildup,

etc. Also, the continuous form of the equations can be solved for voltage switch times, as described in more detail below.

5.0 Generating "Good Moves"

5 The techniques set forth in sections 3 and 4 above determine inputs to a system that utilize substantially the full capabilities of the system actuators and that reduce system vibrations (both mechanical and acoustic). Several techniques can be used, either alone or in conjunction with the techniques presented above, to generate (or enhance) system inputs to reduce system
10 vibrations even further.

 For the purposes of the subject application, a "good move" is defined as a movement of a system component along a trajectory from an initial position to a nominal final position, such that, at the time the component reaches its nominal final position, the component is vibrating at or below an acceptable
15 level, possibly subject to one or more predetermined constraints. In the context of computer disk drives, this means that, as soon as the drive's head reaches its nominal final position, the head is ready to perform a read/write operation to a recording medium. A good move is also one in which acoustic noise excited by the move is at or below an acceptable threshold. In contrast, a "bad move" is, for
20 example, a move in which the component is vibrating at an unacceptable level when the component reaches its nominal final position. In the context of computer disk drives, this means that at the time the drive's head reaches its nominal final position, the head is vibrating at a level which is too high to perform a read/write operation accurately. A bad move is also one in which the acoustic
25 noise excited by the move is above an acceptable threshold.

 A powerful result of the approach outlined herein is that a rigid body command may be calculated by one of a number of techniques including equations 19 or the current mode technique of section 3.1. Next, other dynamics, such as flexible modes, acoustic modes or other dynamic effects can be
30 subsequently corrected by the various methods set forth below. For disk drives,

the process comprises, e.g., determining, over a population of drives and for each move length (or range of move lengths), which frequencies can be heard and which effect settling time. Then, moves may be generated that limit the amplitude of those frequencies or some subset thereof. Frequencies that only
5 appear in a subset of the drives may also be included or turned-on selectively. The effects of the selected frequencies can be reduced by applying any of the techniques set forth below.

5.1 Vibration Limiting and Sensitivity Constraints

10 This technique for generating a good move incorporates physical constraints into a system model. One such model comprises partial fraction expansion equations 19 derived above. To generate a good move in accordance with this technique, the first step is to choose one or more physical constraints. Examples of physical constraints include constraints that limit vibration (both
15 mechanical and acoustic) and constraints for insensitivity to parameter variations.

Constraints for insensitivity to parameter variations can be added to the system equations in several ways. For example, derivatives of the partial fraction expansion equations can be taken with respect to a particular parameter and then added to the constraint equations. This technique is set forth in detail in
20 U.S. Patent No. 5,638,267, issued to Singhose et al. on June 10, 1997, the contents of which are hereby incorporated by reference into the subject application as if set forth herein in full, and in U.S. Patent No. 4,916,635, issued to Singer et al. on April 10, 1990, the contents of which are also hereby incorporated by reference into the subject application as if set forth herein in full.
25 Additionally, a sampling technique can be used to set a series of constraints for different values of a given parameter so as to limit the solution for a variation in that parameter. For example, using this technique, 10% insensitivity at 1000 Hz can be achieved by setting constraints at 900 Hz, 920 Hz, etc. up to at least 1100 Hz. One variation of this technique is set forth in U.S. Patent No. 5,638,267.

In accordance with the invention, constraints can be chosen so as to reduce system vibrations by substantially 100% or to limit reduction in system vibrations to a percentage which is less than 100%, say, between 50% to 70%. Which constraints are used to reduce system vibrations by such amounts can be determined experimentally or by running a computer simulation for the system. Choosing constraints that reduce system vibrations by less than 100% (e.g., a range of 50% to 70%) is particularly useful in cases where excessive vibrations do not occur in the system and in cases where large reductions in vibrations, including noise-inducing vibrations, are not required. In these cases, since the constraints are more relaxed, the resulting system input is shorter in duration. As a result, the system moves faster than it would otherwise. In general, there is a trade-off between move time and the use of stringent constraints. That is, while the use of more stringent constraints may further reduce vibrations, move time is slowed as a result of their use.

Vibration constraint equations may also need to be scaled in order to achieve desired vibration reductions. Specifically, in terms of the foregoing model of a disk drive system, equations for vibration amplitude are relative. This is because the rigid mode equations do not take into account flexible body equations (described below in section 6.3). If a full set of equations (i.e., both rigid and flexible body equations) were derived for the system, and then a partial fraction expansion applied thereto, the coefficients of the vibrational terms would scale to the problem. However, since the equations were derived separately and later combined using the techniques described herein, the relative scaling is not known for the equations given above, and the problem must be scaled manually. In the case of zero vibrations, no scaling is necessary. For any other case, one of several scaling methods may be used. For example, an arbitrary gain may be selected and a resulting sequence applied to the system. The resulting vibrations can then be measured and the vibration constraint equations multiplied by a ratio of a predicted vibrational level divided by an actual measured vibrational level.

By way of example, consider the fourth order transfer function shown below in equation 20. The transfer function corresponds to the position response of a simple mass-spring-mass system to a force input.

$$H(s) = \frac{C}{s^2} * \frac{\omega^2}{s^2 + 2z\omega s + \omega^2}$$

The first term of the transfer function, namely

$$\frac{C}{s^2},$$

corresponds to the rigid body motion, while the second term, namely

$$\frac{\omega^2}{s^2 + 2z\omega s + \omega^2},$$

corresponds to a vibratory mode with undamped natural frequency “T” and damping ratio “z”. When transfer function 20 is expanded in a partial fraction form, the following three terms result:

5

$$H(s) = \frac{-2zC}{\omega s} + \frac{C}{s^2} + \frac{C(-\omega + 4z^2\omega + 2zs)}{\omega(s^2 + 2z\omega s + \omega^2)}.$$

The third term from equation 23, namely,

$$\frac{C(-\omega + 4z^2\omega + 2zs)}{\omega(s^2 + 2z\omega s + \omega^2)},$$

10 corresponds to the transfer function of the vibratory mode, and should be compared to the second order vibratory term included in the original transfer function. Using inverse Laplace transformation, the time domain impulse response of the vibratory mode is determined as

15

20

$$\frac{-C e^{-z\omega t} \sinh(\omega \sqrt{-1+z^2} t)}{\omega \sqrt{-1+z^2}} + \frac{2C z^2 e^{-z\omega t} \sinh(\omega \sqrt{-1+z^2} t)}{\omega \sqrt{-1+z^2}} + \frac{2Cz e^{-z\omega t} \cosh(\omega \sqrt{-1+z^2} t)}{\omega}.$$

Using suitable trigonometric identities, the time domain response of the vibratory mode in equations 25 can be simplified as follows:

$$\frac{-C e^{-z\omega t} \sin(\omega_d t)}{\omega_d} + \frac{2C z^2 e^{-z\omega t} \sin(\omega_d t)}{\omega_d} + \frac{2Cz e^{-z\omega t} \cos(\omega_d t)}{\omega},$$

5

or, after collecting terms, to:

$$C e^{-z\omega t} * \left[\frac{(2 z^2 - 1) \sin \omega_d t}{\omega_d} + \frac{2z \cos \omega_d t}{\omega} \right],$$

10

where “ T_d ” is the damped natural frequency

$$\omega_d = \omega \sqrt{1 - z^2}.$$

The impulse response expression derived above can be used directly to form a quantified constraint equation; i.e. the magnitude of the constraint equation can be set to be less than or equal to an actual vibration level in position.

15

It should be noted that the general form of equation 27 is a phase shifted sine wave of frequency T_d . The sine wave is further subject to a decaying exponential envelope with time constant

$$\frac{1}{z\omega}.$$

5

Equation 27 can be rewritten again, including the phase shift N and scale factor C_1 , as follows:

10

$$C_1 e^{-z\omega t} \sin(\omega_d t + \phi).$$

This form of equation 27 should be compared with the expression for the impulse response of an isolated second order system (as defined by the second term of the original transfer function $H(s)$

$$\frac{\omega^2}{s^2 + 2z\omega s + \omega^2})$$

15 shown below:

$$\frac{\omega}{\omega_d} * e^{-z\omega t} \sin(\omega_d t + \phi) .$$

Since we are only concerned with the magnitude of the residual vibration, phase shift N is of no importance, and the expression for the isolated second order system can be used in the formulation of quantified constraints if the scale factor T/T_d is replaced by C_1 . Parameters C_1 , zT and T_d can be determined experimentally by (i) subjecting the actual system to an impulse input, and from experimental data, (ii) estimating the period of vibration and computing T_d as follows

$$\omega_d = \frac{2\pi}{\tau} ,$$

10

where J is the period, (iii) estimating the decay envelope to determine zT , and (iv) estimating actual amplitude to determine C_1 .

After constraints have been chosen based on the foregoing criteria, a trajectory is digitized and is then solved for each trajectory command value in time subject to the chosen constraints. Digitization of the trajectory results in simpler, and often linear, equations that can be solved readily for the complete system trajectory. The invention, however, is not limited to solving the system equations in this manner. That is, any known technique for solving the system equations can be employed in the context of the present invention. The digitization rate used is a factor that contributes to the successful implementation of the invention. This issue is discussed in section 7.1 below.

20

5.2 Input ShapingTM

This technique for generating good moves uses Input Shaping™ and its substantial equivalents. One example of Input Shaping™ comprises convolving a function with a system input in order to reduce unwanted system vibrations. Examples of system inputs include current and voltage. Specific
5 Input Shaping™ methods are set forth in detail in U.S. Patent Nos. 5,638,267 and 4,916,635, which were incorporated by reference above.

In accordance with this technique, an input to a system, such as a voltage command or a velocity, is shaped in order to produce a desired output. For example, the input may be Input Shaped™ by convolving the input with an
10 impulse sequence which reduces unwanted vibrations in the system, including its flexible modes. Alternatively, the input may be shaped using any one or more of the filtering techniques presented herein, or using any other known command profiling techniques.

15 5.3 Filtering

In addition to Input Shaping™, as noted above, any type of conventional shaping method can be used to generate an input that results in a good move. For example, it is also possible to generate a good move by filtering a trajectory with infinite impulse response (“IIR”) or finite impulse response
20 (“FIR”) filters, including filters where there are zeros near poles of the system, such as those described below.

5.4 Least Squares Solution to Frequency Sampling

A conventional least squares approach can also be used to generate
25 an input that results in a good move for a computer disk drive system. An example of such an approach is provided in U.S. Patent No. 5,638,267. This approach may also be used to limit high mode excitations.

5.5 Selective Shaping™

Input Shaping™, filtering, and the like can increase seek time in
30 some cases. However, the length of an Input Shaper™ is directly related to the

period of the vibration being reduced. At low frequencies, i.e., long periods, the increase in seek time caused by an Input ShaperTM can be a substantial percentage of the total seek time. This is of particular significance in relation to computer disk drives. That is, in computer disk drives, relatively low frequency vibrations can occur due to compliance of the drive's mounting in its enclosure. For example, a 200 Hz mounting resonance will have a period of 5 ms. In this case, a three-pulse Input ShaperTM will also have a period of 5 ms. Thus, if the computer disk drive has an average seek time of 10 ms, the drive's average seek time will increase by 50% if the Input ShaperTM is applied to all moves.

10 In view of the foregoing, it is advantageous to apply Input ShapingTM selectively. This is possible because not all moves result in unwanted vibrations. That is, some moves are inherently good, meaning that they produce relatively few vibrations, and some moves are inherently bad, meaning that they produce excessive vibrations. By evaluating constraint equations for a given move, whether that candidate move is good or bad can be predicted in advance. That is, a move can be evaluated to determine whether the move excites greater than a predetermined level of vibrations in the system. Input ShapingTM can then only be applied to moves that excite greater than the predetermined level of vibrations. Thus, only those moves exciting greater than the predetermined level of vibrations, e.g., the bottom 30% of the moves, need be ShapedTM.

By virtue of the foregoing, the present invention provides the advantages flowing from using Input ShapingTM with less of an increase in seek time than would otherwise be achievable. Moreover, in accordance with the invention, a level of Input ShapingTM, or the numbers and types of constraints, may be altered depending upon how good or how bad a move is, i.e., depending upon the level of vibrations that the move excites. For example, if a move only requires minimal Input ShapingTM, lengths of impulse sequences used to Input ShapeTM the move may be reduced.

In the context of computer disk drives, for a given frequency of interest, a measure of the goodness of a move can be evaluated by examining a

superposition of components of an input at the frequency of interest. An example of such a superposition is shown in the graph of Figure 12, in which the frequency of interest is 200 Hz, and in which a good move/bad move threshold is labeled 81. By examining threshold 81, it is evident that movement distances within a range around 1800 tracks and 7000 tracks are inherently good moves. On the other hand, movement distances requiring vibration reduction are identified in Figure 12 by cross-hatching. For these movement distances, the amount of vibration reduction required is determined by taking a ratio of a move's goodness level to the good/bad threshold. The magnitude of the Input ShaperTM required for each movement distance is determined based on this ratio.

Specifically, the magnitude of an Input ShaperTM response can be equated to a desired reduction in vibrations ("mag") to derive an expression for a modified Input ShaperTM. The expression for the period, τ , of a modified two-pulse ShaperTM is as follows

$$\tau = \frac{\arccos(2 \text{mag}^2 - 1)}{2\pi f}$$

It is noted that the above expression is closed form and, therefore, is suitable for on-line, real-time implementation. For unity magnitude ShapersTM (mag=1) in which no vibration reduction occurs the foregoing expression yields

$$\tau = 0,$$

and the two pulses are co-incident at time $t=0$. For zero magnitude ShapersTM (mag=0) in which 100% vibration reduction occurs, the foregoing expression yields

$$\tau = \frac{1}{2f},$$

or ½ period. At intermediate values of mag, the expression yields intermediate values of the Shaper™ period J. For example, when mag=0.5,

$$\tau = \frac{1}{3f}.$$

5 At this point, it is noted that although two and three impulse Input Shapers™ are described above, the invention can use Input Shapers™ having more than three impulses as well as to shapers designed using other techniques. It is also noted that although the invention has been described with respect to Input Shaping™, any shaping technique may be used. For example, moves that are
10 considered bad moves could be selectively shaped using an FIR filter, an IIR filter, any shaper, or even just extended in some arbitrary way to achieve the goals of the present invention. In addition, constraints, such as vibration limiting constraints or the like, may be selectively added to the system equations based on whether a move has been identified as good or bad, and the resulting set of
15 equations can be solved for a complete move trajectory. The moves also may be solved off-line and tabulated to achieve the same benefit.

5.6 Voltage Control By Forcing Switch Times

20 Disk drives operate in a current command mode, meaning that their operation is controlled by current commands. Since saturation is in voltage, conventionally there is no way to determine if a particular current command will saturate the system (notwithstanding section 3.1 above). Accordingly, commanding the system in current can fail to produce a desired movement. The invention addresses this problem by commanding a current that is guaranteed to
25 saturate a voltage input to the system. In this way, the invention is able to

command voltage in either direction. That is, it is possible to provide current commands to the system, but actually to be commanding voltages switches.

In more detail, many disk drive systems utilize a closed-loop current control system to control current through a voice coil motor. A closed-loop controller in such a system makes it possible to specify a current command that, when applied to the motor, results in a constant torque. Specifically, the closed-loop controller adjusts the voltage through the motor to maintain a desired current level. However, there are limitations to such a controller. Specifically, the maximum voltage available to the controller is limited by the power supply used in the disk drive. Thus, if the voltage required to achieve a particular current is above the power supply's maximum voltage, the controller will saturate at the maximum voltage and the desired current will not be achieved.

While the foregoing may be perceived as a drawback, it can actually be an advantage, since the saturation can be used to operate the current controller in an alternative mode in which power supply voltage is simply applied to the motor's terminals. That is, the controller is operated as an open-loop voltage switching system, instead of as a closed-loop current control system. As a result, it is possible to create an alternative formulation for control strategies and motion profiles. This technique of using current control to command voltage has the additional benefit that voltage commands can be used during disk drive seek; however, a normal current command mode is still available for tracking without changing any system hardware.

Use of the open-loop voltage control technique described above may require a series of precisely-timed commands to achieve vibration suppression effects. Section 7.1 below presents a variety of techniques for implementing such precisely-timed commands. If the commands are not in the fundamental limiting parameter of the system, then section 3.1 may also be used to generate such commands. If the commands are in the fundamental limiting parameter, then the techniques of sections 4 and 5 can be used.

In this regard, the fundamental limiting parameter is often not used to command the system due to hardware constraints (e.g., the tracking controller in a disk drive system is designed for current, not voltage, commands). In the case of a disk drive, by modifying the drive's amplifier, it is possible to use voltage commands during one mode of operation, e.g., drive seek operations, and to switch to current commands during another mode of operation, e.g., drive tracking operations. Thus, for example, the techniques of section 3.1 can be used during a tracking operation and the techniques of sections 4 and 5 can be used during a seek operation.

5.7 Other Techniques

In addition to the foregoing techniques, other techniques may also be used to generate (or enhance) an input to produce a good move. For example, it is possible to adjust any of the above techniques using real-time identification of any system parameters. Specifically, a system parameter, such as temperature or resistance, may be identified, and that parameter addressed when generating a good move. Additionally, symmetric and multi-step (i.e., Posicast) inputs can be used to generate a good move. As set forth in section 11 below, transient portions of the input or feedforward signal at the beginning, middle and/or end of a move may also be varied in order to reduce vibrations resulting from the move. Additional constraints may also be added to the system in order to control vibrations. For example, these constraints can be symmetric and can be a function of time or position and/or can relate to thermal limits, current limits, duty cycle, and/or disk drive ZV constraints. Moreover, it is noted that since each transition of an input corresponds to a complete move in and of itself, any of the above techniques for generating a good move set forth above can be performed in real-time, and the ShapingTM and filtering methods described above can be performed only on the rapid transient portions of the move. See section 11 below.

The ShapersTM and filters described above are preferably stored in a memory as computer-executable process steps, and executed by a processor in the system. However, the invention can also be implemented in a fuzzy logic controller by embedding either an Input ShaperTM or direct solutions to systems of constraint equations in a fuzzy logic block. Similarly, the invention can be implemented in a neural network controller that can be constructed by imbedding either an Input ShaperTM or direct solutions to systems of constraint equations into a neural network. Both the fuzzy controller and the neural network PV controller can be designed to handle non-linear system parameter variations which enter into equations for a system.

6.0 Controlling Trajectory as a Function of Time

This aspect of the invention is directed to a control technique for reducing unwanted vibrations in a dynamic system by controlling a trajectory which is specified as a function of time. More specifically, in this aspect of the invention, an input that corresponds to a good move is used as feedforward trajectory for the system. Any of the above techniques for generating inputs corresponding to a good move may be used to modify inputs in the following control system. However, for the sake of brevity, only Input ShapingTM will be described in detail. Moreover, although the invention can be used to control any dynamic system, a description will be provided only for a computer disk drive system, again for the sake of brevity.

6.1 Optimization

One approach to generating an input that will result in a fast response in a computer disk drive is to perform an optimization using partial fraction expansion equations 19. To perform the optimization, these equations are augmented by including a set of constraints to address vibrations in various modes of the system. In addition, constraints may be added for vibrations in modes that are near a predicted vibrational mode and for real world conditions, such as

voltage limits. A digital formulation of the problem can then be modeled so as to make all of the constraints linear, thereby simplifying their solution. The digitization rate may be selected using the techniques presented in section 7.1.

The invention is not limited to methods for performing optimization described herein. Rather, any optimization technique may be used. For example, other methods for implementing optimization which can be used in conjunction with the present invention include off-line computation and use of efficient linear solving codes on the disk drive controller. It is also possible to generate a series of solutions off-line and to fit curves to the solutions. Appendix C shows a set of linear equations written in GAMS that can be solved for ZVD constraints on a problem in which voltage is the commanded input.

6.2 A Related Approach

The partial fraction expansion model of a disk drive system shown above can also be used in conjunction with Input ShapingTM in order to generate system inputs. For example, in an article entitled "Fast Servo Bang-Bang Seek Control" by Hai T. Ho, ©1997, IEEE, the contents of which are hereby incorporated by reference into the subject application, it was demonstrated that near the end of a move, the instantaneous state of a system can be measured. Inputs to the system can then be calculated so as to bring the system to its final location with limited vibrations. The flaw in this technique, as presented in the article, is that exact solutions to the disk drive system equations could not be obtained because a second order system model was assumed. Since a disk drive system is more accurately modeled as a third order system, this technique could result in inputs which did not sufficiently limit vibrations or which resulted in the system reaching a nominal final position without coming to rest. By use of the partial fraction expansion model presented in section 4, a more precise solution to the system equations can be obtained, thereby resulting in relatively fewer vibrations when the system reaches its final location. Moreover, insensitivity constraints can be added to the foregoing equations by a variety of techniques,

e.g., by sampling (as discussed in section 6.7), by taking derivatives (as discussed in U.S. Patent No. 4,916,635), or any other approach, thereby leading to robust solutions of the equations and still fewer resulting vibrations.

5 6.3 Rigid and Flexible Mode Problem

Another approach which uses Input ShapingTM in conjunction with the partial fraction expansion model of section 4 is to separate the problem into a rigid mode problem and a flexible mode problem. Examination of modal terms associated with a disk drive reveals terms similar to a third order system, e.g.,
10 $F_1(t)$, $F_2(t)$ and $F_3(t)$ from equations 12, plus additional terms associated with oscillating or vibrational modes, e.g., $F_4(t)$, $F_5(t)$, etc. (not shown). The present invention separates these terms into two sets. The first set, which defines the rigid mode of the system, includes the third order system modal terms, i.e., $F_1(t)$, $F_2(t)$ and $F_3(t)$. The second set, which defines the flexible modes of the system,
15 includes the other modal terms, i.e., $F_4(t)$, $F_5(t)$, etc. The partial fraction expansion equations in section 4 can be solved for inputs which drive the system so as to satisfy rigid body motion constraints $F_1(t)$, $F_2(t)$ and $F_3(t)$ and thereby achieve a final position with substantially zero velocity and acceleration. However, vibrations resulting from the other modes, namely $F_4(t)$, $F_5(t)$, etc., can
20 still be problematic.

More specifically, the partial fraction expansion equations cannot be solved for an input which reduces vibrations in the flexible modes without adding additional constraints for each additional mode. However, adding additional constraints increases the complexity of obtaining the solution.
25 Additionally, if curve fit or empirical solutions are to be obtained, the solution is increasingly more complicated for each additional constraint that is imposed. Therefore, in order to reduce vibrations in the flexible modes without substantially increasing the complexity of obtaining a solution, the present invention first solves the rigid mode equations in order to determine system
30 inputs. Next, the determined system inputs are shaped using an Input ShaperTM

designed for the flexible modes of the system. For example, the Input Shaper™ may be designed based on frequency and damping ratios of $F_4(t)$, etc. above.

The partitioning of $F_1(t)$, $F_2(t)$ and $F_3(t)$ into the rigid mode and $F_4(t)$, $F_5(t)$, etc. into the flexible mode is merely an example of one way to partition the system's modeled modes. The invention is not limited to such definitions. In fact, the partitioning of modes can vary depending upon the system under consideration as well as various other factors. For example, it is possible to derive a second order system input based on a system model that includes only $F_1(t)$ and $F_2(t)$ in the rigid mode and that includes $F_3(t)$, $F_4(t)$, etc. in the modes that are addressed using Input Shaping™. Such a formulation would be of particular advantage in the case where $F_3(t)$ corresponds to a system's electrical time constant, since Input Shaping™ could be used to correct variations in the system's electrical time constant.

6.4 Center Of Mass

In the rigid mode of a system, problems may arise because various components of the system are moving relative to one another. For example, in the case of a computer disk drive, vibrations may be induced in the system because the motor's rotor is moving out of phase with an endpoint, such as the read/write head. This will cause problems during feedback if a rigid body model is assumed. That is, if the endpoint alone is used as feedback, the deflection that is observed will be fed back and cause corrections that are not required and thus may be detrimental to system performance. To reduce such errors, the present invention estimates the center of mass of the system and uses the estimated center of mass, rather than an endpoint, as the system's feedback. One way to estimate the center of mass of the system is to calculate a state estimator using modern control techniques. A wide range of correction factors, such as a quasi-static correction factor similar to that described below, can be applied to improve the estimate of the center of mass coordinate.

The center of mass coordinate estimated above will not reflect the vibrations of the rotor nor those of the endpoint. Consequently, the rigid body behavior of the system can be decoupled from most all vibrations (including acoustics) in order to allow for more accurate feedback control than has heretofore been possible.

6.5 Quasi-Static Correction

On the other hand, if endpoint feedback, rather than center-of-mass feedback, is used in the system, vibration-reducing inputs to the system, such as those generated in accordance with the techniques set forth herein, can cause unusual side effects. That is, the component at the endpoint (e.g., the head in the case of a disk drive) does not vibrate. Rather, the component deflects during the move. The deflection is in one direction during acceleration phases and in another direction during deceleration phases. The feedback signal to the controller is measured based on this deflection. As a result, if the system controller uses this feedback signal to compare to a trajectory, the controller will detect an error even if none exists. To correct this problem, a quasi-static correction factor may be added to, or subtracted from, the feedback signal depending on the amplitude and the direction of acceleration.

6.6 Closed-loop Control

By adopting a control strategy in which a trajectory is specified as a function of time, a closed-loop system formulation can be made. As shown, for example, in Figure 11, feedback loops may be closed around any combination of system states. In the case of a disk drive, these states include voltage, current, acceleration, velocity, and position. An input which corresponds to a good move can then be generated based on the closed-loop formulation. This "good" input, which, in the case of a computer disk drive, may be a voltage input, is used to generate feedforward signals to some or all of the closed-loops.

Feedforward trajectories for each of the parameters to be used as a feedforward term are derived from a trajectory selected as a "good" move. The technique for generating feedforward trajectories may be based on either a simple simulation of the system or the partial fraction expansion model set forth in section 4. When generating a good input, it may be desirable to compute a move assuming that less voltage (or whatever physical variable is limited by reality) is available. This increases the chances that the system will stay on a trajectory corresponding to the good move. Another approach to generating a good input is to assume full voltage (or whatever physical variable is limited by reality) and to assume safe values for the physical system parameters used in the model. In this case, full voltage would only be used if the parameters were the worst case possible. At all other nominal cases, a lower voltage would be used.

In the closed-loop control model, the feedforward terms for each loop could be replaced by only one feedforward (or input) to the outer loop, where this one feedforward term is computed as a combination of each of the other feedforward terms. Also, feedforward inputs for the system could be scaled differently for each system parameter. For example, different gains could be used for each of velocity, position, acceleration, current, and voltage feedforward terms. The selection of gains adds zeros to each feedforward term. Since Input ShapingTM is a method of placing zeros in certain locations using a constraint based technique, it is understood that the gains selected for the feedforward terms can be chosen to add zeros which serve to augment Input ShapingTM. This technique would lower the requirements on any Input ShaperTM used, or enable fewer constraints to be used in the derivation of complete trajectories.

Shown in Figure 27 is a block diagram of a simple system, namely system 82, that will be used to demonstrate how a collection of feedforward signals can be used to effect zeros in a transfer function. In system 82, the variable to be controlled is the output position x , there is a feedforward input FF , and there are three command inputs, namely position input x_d , velocity input v_d , and acceleration input a_d . There is also full state feedback of position x , velocity

v, and acceleration a. In the ideal case, the feedforward input FF will cause the system to follow a desired trajectory (x, v, a) through state space. If the actual trajectory does not match the desired trajectory, then error terms ($x_d - x$), ($v_d - v$) and ($a_d - a$) will be multiplied by gains K_a , K_v and K_a to generate corrective inputs. If the inputs v_d , a_d and FF are all set to zero, the system will still "track" the remaining command input x_d , but likely with larger position error.

The command inputs, x_d , v_d and a_d , and the feedforward input FF are produced by another process and are simply inputs to the system. However, the command inputs x_d , v_d and a_d are mathematically related as derivatives. Their relationship is indicated in the block diagram shown in Figure 28 by applying the Laplace differentiation operator "s" repeatedly to the x_d input signal. It is well known that it is physically impossible to implement the zero corresponding to the "s" operator without a corresponding pole. Since the input signals v_d and a_d are actually derivatives, the use of the "s" notation in Figure 28 is a notational convenience facilitating intuition, not a means of implementation.

By applying block diagram algebra to the block diagram shown in Figure 28, scaled versions of all the inputs (x_d , v_d , a_d and FF) can be shown to enter the closed-loop system at a single point, as shown in Figure 29. The combination of the three parallel inputs (to the nominal closed-loop system) shown in Figure 29 can be reduced further using block diagram algebra as shown in Figure 30. The numerator of the block shown in Figure 30 is a third order zero. For this system, the zeros associated with the combination of feedforward terms exactly match (and cancel) the poles of the nominal closed-loop system. Thus these zeros serve to cancel the dynamics of the modeled system. The location of the zeros can be adjusted by including weighting factors W_v , W_a and W_f on each of the terms v_d , a_d and FF, respectively. Following through with the analogous block diagram reduction yields the result shown in Figure 31.

By allowing additional freedom in the placement of the zeros (by adjusting weights W_v , W_a and W_f), the zeros can be placed to effect a first order cancellation of the (un-modeled, but measured) poles of the system, e.g. poles

associated with vibration or other unwanted dynamic response. Since FIR input shapers can be viewed as “all zero” filters, the zeros associated with the weighted feedforward input can be used to replace or augment the action of the zeros of the FIR input shaper. Thus, since some zeros are supplied by the weighted feedforward input, a lesser number of zeros must be supplied by the shaper, and consequently, the shaper period becomes shorter. The overall time advantage lies in the fact that the zeros associated with the weighted feedforward are implemented without a time cost (i.e., without a penalty).

6.7 Additional Constraints

It is also possible to add constraints to the partial fraction expansion equations of section 4 in order to provide for relatively rapid movements of the rigid mode portion of the system. For example, it is possible to add constraints relating to insensitivity to variations in system parameters. To do this, one or more constraint equations in the continuous form of equations 19 may be differentiated with respect to the system parameter and the resultant set to zero. This ensures that the solutions to the equations are insensitive to variations in that parameter. A similar result can be obtained by solving the equations to which insensitivity is required multiple times with different values for the system parameter. For example, the second of the above partial fraction expansion equations 19 can be repeatedly solved with different torque constant values in order to assure that the solution thereto works well for a range of torque constant values. Such an equation must be given some degree of freedom by not requiring that the solution be exactly zero for all values of torque constant.

6.8 Switch Times

As noted above, the continuous form of the partial fraction expansion equations can also be solved for voltage switch times which reduce vibrations in the system. A voltage switch time corresponds to a transition time between full positive and full negative voltage inputs to the system. In solving for

these switch times, if no other constraints are included, the system can be modeled using the three partial fraction expansion equations 19 shown above in section 4. Using the continuous version of these equations, it is possible to solve for three transition times, namely t_1 , t_2 and t_{end} , as set forth below.

5 Equations 19 are nonlinear in their continuous form. However, they can be manipulated to make them easily solvable in a controller with limited computational power. Since the first equation is linear, the first equation can be substituted into the other equations, yielding two equations with two unknowns. The solution can then be obtained by performing a simple fixed-point iteration.
10 Only a few iterations are needed to obtain a solution to machine precision. Additionally, the starting guess for the iteration can be obtained from a simple curve fit, thus further increasing the speed of the calculation process. It is also possible to generate solutions to these equations by defining switch times as a function of movement distance and then fitting the data with an empirical formula
15 to achieve a solution that is sufficient for use in a digital controller.

 To this end, an additional step that is performed in order to use the continuous switch time solution in a digital controller is to round-off the switch times to a nearest digital time spacing. However, because significant errors can be generated by rounding-off the switch times, another approach is often used.
20 The switch times are rounded upward and the voltage levels in each region are adjusted to achieve a solution to the same equations. Alternatively, voltage levels in only a portion of the solution are adjusted in order to achieve the same result. For example, only a few digital outputs are adjusted to correct for the round-off.

 The pseudo-code shown in Appendix A illustrates (i) the
25 calculation of continuous switch times, (ii) a method of rounding the continuous switch times to discrete time intervals, and (iii) recalculation of the voltage levels to satisfy the original constraint equations including discrete switch times. In the first section of the pseudo-code, the physical system parameters (V_{max} , K_t , K_b , I , k , R_e , R_m , and J_m) are used to compute transfer function parameters (A , a , b). While
30 in theory this step is not required (a formulation in the original system physical

parameters could be used), the resulting equations are much more compact and more suitable for real-time implementation.

In the formulation shown in Appendix A, the accommodation of digital switch times requires that the entire voltage level of each of the three steps be modified in order to satisfy the constraint equations. Modification of the entire step resulted because of the specific formulation in terms of three steps in voltage. If the problem is reformulated, e.g. in discrete impulse response form corresponding to partial fraction expansion equations 19 (repeated below as 38 for convenience), other, more flexible modifications of the voltage wave form are possible.

$$\begin{aligned}
 Finalpos &= \sum_{i=1}^N V_i A \Delta t \\
 0 &= \sum_{i=1}^N V_i \frac{Ab}{b-a} (e^{-a(T_{end}-T_i+\Delta t)} - e^{-a(T_{end}-T_i)}) \\
 0 &= \sum_{i=1}^N V_i \frac{Aa}{a-b} (e^{-b(T_{end}-T_i+\Delta t)} - e^{-b(T_{end}-T_i)})
 \end{aligned}$$

The pseudo-code shown in Appendix A can be used to compute the digital switch times (rounded from continuous), and the impulse response form of the constraint equations used only for the final adjustment of voltage levels. A voltage variable for the reformulated voltage adjustment problem can be formed by selecting an individual V_i , or alternatively selecting a dependent set of V_i (e.g. $V_1=V_2=V_3=V_{first}$). The three constraint equations form a linear set of three equations in the three variables and can be solved using any method suitable for linear equations. If more than three variables are chosen, then the solution will not be uniquely determined and opportunity exists for additional criteria to be used to select from among the possible solutions.

6.9 ShapedTM Switching

According to the well-known bang-bang principle, time-optimal system commands for a voltage-limited system like a computer disk drive comprise a series of full-positive and full-negative voltage commands. In such a case, the voltage levels are known, but their optimal switch times are not. Because optimal switch times for the system are unknown, it is likely that unwanted vibrations will be excited when the voltages commands are input to the system. Several techniques for reducing unwanted system vibrations can then be performed. For example, it is possible to determine a switching sequence analytically, subject to various constraints, such as vibration constraints, insensitivity constraints, or any number of unwanted dynamic or physical system constraints. Additional techniques that can be used include determining switch times using any technique described herein and adjusting the switch times in real-time to take system movements into consideration.

Another effective technique for commanding a disk drive to move is to combine the benefits of a bang-bang time-optimal command with the benefits of Input ShapingTM. To this end, switch times for an input to a rigid system are determined analytically, and then an Input ShaperTM is applied to the input in order to shape it so that unwanted vibrations resulting therefrom are substantially suppressed. This technique has at least two advantages. First, it is relatively easy to implement from a computational point of view because the problem is separated into two problems, namely generating a good input for a simple system and separately generating a good ShaperTM to handle flexible, and possibly some rigid, modes. Second, solutions obtained by separately ShapingTM the input are more insensitive to system parameter variations.

Shaping of the input may be performed in a manner described above using, e.g., an Input ShaperTM, a filter, etc. Accordingly, a detailed description of shaping the input is omitted here for the sake of brevity. With regard to generating a good input, since voltage levels for the input are already known (i.e., the voltage levels are either full positive and full negative), the only

variables that need to be determined are switch times for the voltage input. Switch times can be determined using a partial fraction expansion model of a system, such as equations 19, in which $F_1(t)$, $F_2(t)$ and $F_3(t)$ correspond to step responses to a unit voltage in each mode of the system. For a third order model

5 such as this, three transitions between full positive and full negative are required. Switch times, namely t_1 , t_2 and t_{end} , for the transitions are determined as follows.

Using equations 14, reproduced below as 39,

$$\begin{aligned} X F_1(t_{end}) &= V_0 F_1(t_{end} - t_0) - 2V_0 F_1(t_{end} - t_1) + 2V_0 F_1(t_{end} - t_2) \\ X F_2(t_{end}) &= V_0 F_2(t_{end} - t_0) - 2V_0 F_2(t_{end} - t_1) + 2V_0 F_1(t_{end} - t_2) \\ X F_3(t_{end}) &= V_0 F_3(t_{end} - t_0) - 2V_0 F_2(t_{end} - t_1) + 2V_0 F_1(t_{end} - t_2), \end{aligned}$$

and constraint equations 15, reproduced below as 40,

$$\begin{aligned} X F_1(t_{end}) &= Finalpos \\ X F_2(t_{end}) &= 0 \\ X F_3(t_{end}) &= 0, \end{aligned}$$

10 it is possible to solve for the three unknown transition times t_1 , t_2 and t_{end} . A change of variables, i.e.,

$$\begin{aligned} et_1 &= t_{end} - t_0 \\ et_2 &= t_{end} - t_1 \\ et_3 &= t_{end} - t_2, \end{aligned}$$

further simplifies the solution for the switch times. In this case, et_1 corresponds to an elapsed time from onset of a first step until the end of the move, et_2 corresponds to the elapsed time from onset of the second step until the end of the

15 move, and et_3 corresponds to the elapsed time from onset of the third step until the end of the move.

In view of the foregoing, equations 39 reduce to the following:

$$Finalpos = V_0 F_1(et_1) - 2V_0 F_1(et_2) + 2V_0 F_1(et_3)$$

$$0 = V_0 F_2(et_1) - 2V_0 F_2(et_2) + 2V_0 F_1(et_3)$$

$$0 = V_0 F_3(et_1) - 2V_0 F_2(et_2) + 2V_0 F_1(et_3).$$

Since equations for $F_1(t)$, $F_2(t)$ and $F_3(t)$ contain exponential terms, a numerical solution to the above equations for $XF_1(t_{end})$, $XF_2(t_{end})$ and $XF_3(t_{end})$ is not readily available. However, certain simplifications can be made to the equations in order to provide an iterative numerical solution, and thus to allow them to be solved for transition times t_1 , t_2 and t_{end} in real-time. More specifically, the duration of the third step of the input to a third order system does not vary significantly for relatively long moves. Therefore, for long moves, the third step duration is nearly independent of values of et_1 and et_2 . Accordingly, the second equation (for $XF_2(t_{end})$) can be solved for et_3 using guesses for et_1 and et_2 . The value of et_3 obtained in this manner is a close approximation to its exact value. The first equation (for $XF_1(t_{end})$) is used to eliminate et_1 from the third equation (for $XF_3(t_{end})$), whereafter the third equation is solved for et_2 as a function of et_3 . The value obtained for et_2 is also a close approximation of its exact value. The first equation is then used to calculate an approximation for et_1 based on the approximate values of et_2 and et_3 . If more accuracy is desired, another pass may be made through the equations. That is, the approximations calculated for et_1 and et_2 can be substituted back into the foregoing equations, and the process repeated for several iterations, where each iteration provides an increase in accuracy. In practice, four iterations through the equations resulted in 16 digit accuracy for et_1 , et_2 and et_3 . Once these values are determined, values for the transition times t_1 , t_2 and t_{end} can be calculated using the equations shown above.

The iterative solution presented above for determining switch times will converge faster for better initial guesses of et_1 and et_2 . On short moves especially, convergence can be slow if initial guesses for et_1 and et_2 are not good. Accordingly, there exists a need for a way to provide a good initial guess. One

such technique is to tabulate solutions for a range of short moves. Such a table may be then used to obtain a good guess, e.g., by looking-up a guess or by interpolation. Alternatively, a curve can be fit to solutions for a range of short moves, and initial guesses determined based on the curve. For example, it has
5 been determined experimentally that a first switch time is a monotonically increasing function of move distance. Curves for other switch times can be determined in a similar manner.

The foregoing techniques for determining switch times can be expanded to include parameters other than just movement distance. For example,
10 if resistance change is to be included in the solution, an initial guess for a switch time value can be determined based on both movement distance and resistance. Any number of system parameters can be used in this manner to determine an initial guess. In such cases, the initial guess can be determined based on a multidimensional table which includes these parameters, or computed using an
15 empirically generated function. Switch times can also be generated by taking into account system parameters in addition to those set forth above. In such cases, conservative parameters may be used so that the actual system will move faster than the theoretical model on which the switch times are based. That is, in this case, the feedback will scale back the output voltage and the system will almost
20 never be commanded past saturation.

As an alternative to the above approaches which rely on an initial guess, short move solutions can be determined based on the partial fraction expansion equations. Specifically, the exponential terms of the partial fraction expansion equations can be expressed in series form. The equations can then be
25 solved for the short move solutions to the switch time problem.

A hardware implementation of this embodiment of the invention may be dictated by the design of many disk drive controllers. Specifically, in such disk drive controllers, the update rate of a processor in the controller is not fast enough to output voltages at precise desired time intervals. Accordingly, a
30 hardware solution may be implemented, in which each next switch time is loaded

into a hardware counter chip and a high frequency clock counts intervals until the desired switch time is achieved. At such time, the output of the counter chip changes and the new voltage value is output to the disk drive system.

Still another alternative to the forgoing method for determining switch times for a system input is provided in U.S. Provisional Application No. 60/076,951, entitled "Creating Time-Optimal Commands For Linear Systems", filed on March 5, 1998 and its corresponding national application filed concurrently herewith. The contents of these two applications are hereby incorporated by reference into the subject application as if set forth in full.

7.0 ShapingTM Near or Beyond Nyquist

As noted above, control techniques in which trajectory is specified as a function of time involve determining an input which will generate a good move. As also noted above, this input may be determined using any other techniques, such as Input ShapingTM, filtering, etc. In addition to these techniques, the present invention also provides a technique for shaping inputs having frequencies near or beyond the nyquist frequency. ShapersTM used to perform this shaping are referred to herein as "NBN" ShapersTM.

Systems that use discrete time or digital control face a fundamental limitation due to the effects of sampling. That is, the sampling theorem states that any frequencies greater than the sampling frequency (or Nyquist frequency) will be aliased to other frequencies. Therefore system feedback control cannot suppress vibrations that are at a frequency greater than the Nyquist frequency. Because Input ShapingTM is a feedforward technique, it does not have this same limitation. Input ShapersTM can be designed to suppress vibrational frequencies that are near, or even well above, the Nyquist frequency. This section will demonstrate how to design Input ShapersTM which limit vibrational frequencies that are near or above the Nyquist frequency.

As background, disk drives systems with embedded servo information have a maximum position update rate that is determined by the

density of the servo information and the drive's rotation speed. To demonstrate the difficulty in solving for an Input ShaperTM, an example drive is presented. Assuming that the servo information on such a disk drive is updated at 5 KHz, and the drive's first resonant mode is at 2 KHz, only 2+ servo cycles exist for each vibrational cycle. This presents a computational problem. That is, only 2 unknowns exist per servo cycle and there are many more constraints to be solved (at a minimum no vibration constraints, among others). Accordingly, the problem is over-constrained.

However, more than one cycle can be used to solve for a system input. By expanding the number of unknowns until the problem becomes solvable, a solution can be obtained. Solutions obtained are unusual because they take more than one cycle of vibration to reduce vibrations to an acceptable level. Additionally, careful attention must be paid to insensitivity constraints because NBN solutions will be less sensitive than conventional solutions since fewer cycles of vibration are allowed to occur before cancellation. An alternative to this approach is to use an output or feedforward command rate that is different from the servo rate. This technique is presented in section 7.1 below.

The basic principle of the NBN shaper can be understood by examining the design of a three pulse shaper for a continuous system with zero damping. If we assume that the system is continuous, the shaper impulses can occur at exact times. When the damping ratio is zero, the amplitudes of the impulses for a three pulse shaper are [.25 .50 .25]; the first pulse occurs at time zero, the second pulse at one half period of vibration, and the third pulse at one period of vibration. Figure 32 shows a plot of the impulses of the three pulse shaper along with a sine wave representative of the undamped vibration. The combined plot shows the phasing of the impulses relative to the sine wave. In the continuous case, the pulses occur at the times shown in Figure 32. In the digital case, the pulses are constrained to occur at integer multiples of the sample period, i.e. at the sample times. If the sample period is much shorter than the vibration

period, then each of the shaper pulses can be split between the nearest sample times to achieve the same effect.

The Nyquist rate is equal to one half the sample rate and represents the lowest frequency that can be sampled by a digital system without alias. Thus, vibration occurring at the Nyquist rate is just at the theoretical limit of what input can be processed by a digital system without alias, and results in two sample points per sine wave period. Two sample points per period is exactly the ideal spacing for a three pulse shaper. Figure 33 shows a plot of the digital pulse spacing for a three pulse shaper where the digital sample rate (4 KHz) results in the Nyquist rate ($\text{sample_rate}/2 = 2 \text{ KHz}$) being equal to the vibration frequency (2 KHz). Thus, the three pulse shaper is easily implemented to attenuate frequencies at the Nyquist rate.

It is well known that vibration with frequency in excess of the Nyquist rate cannot be sampled by a digital system without aliasing, and that therefore a closed-loop digital sampled data system cannot use closed-loop control techniques to attenuate vibration at high (beyond Nyquist rate) frequency. However, the open-loop (feedforward) shaping technique can be applied to attenuate vibration at frequency well beyond the Nyquist rate. Shown in Figure 34 is the pulse spacing for a three pulse shaper and a sine wave representative of vibration. The combined plot shows the timing of the shaper pulses relative to the phasing of the sine wave. The frequency of vibration is again 2 KHz, the sample rate for this example is 1.333 KHz, and the associated Nyquist rate is $1.333\text{KHz}/2 = 0.666\text{KHz}$. The frequency of vibration is well in excess of the Nyquist rate ($2\text{KHz}/0.666\text{KHz} = 3$) for this case.

Examination of the phasing of the sine wave relative to the timing of the shaper pulses reveals the same relation for the sub-Nyquist rate example as for the Nyquist rate example. That is, the first shaper pulse occurs at 0° , the second shaper pulse occurs at 180° and at each 360° thereafter, and the third shaper pulse occurs at 360° and at each 360° thereafter. Since the sine wave phase repeats each 360° , the superposition of responses yields the same result in

both cases. It should be noted that the sub-Nyquist rate shaper will be more sensitive to errors in the vibration frequency estimate. The increased sensitivity is due to the fact that as more periods of vibration elapse between pulses, larger errors in phase (for a given error in frequency) will accumulate.

5

7.1 Effect of the Rate of Command Output

The rate that is chosen for issuing digital commands to the system is extremely important. A rate should be chosen that makes sense for the particular system being considered. In some cases, this rate is simply the servo rate of the control system. However, for disk drives, this rate must usually be higher because of the restrictions imposed by the use of embedded servo information for control. For systems in which the highest frequency of vibration to be suppressed is considerably lower than the servo rate, the servo rate is adequate for use as an output rate. For systems such as those considered in section 7.0 (such as most disk drives), the rate must be higher.

One approach is to send output commands to the system at a multiple of the servo rate. In this formulation, the output to the physical system might be performed at two, three, or more times the rate of the servo. In our example system, the servo rate is 5KHz. The highest mode to be suppressed is 2KHz. If the output to the system is performed at triple the servo rate (15KHz), there are over seven digital outputs per vibration cycle; therefore, the shaping formulations become simple. Several possible architectures can be considered. Two possibilities are presented below.

In the first example, there is a separate output path from the controlling computer chip to the hardware for feedforward purposes. An example of this is a disk drive in which a voltage command can be fed forward directly to the amplifier while current commands are output by the closed-loop servo. In order to actually implement this, the following steps must be performed. At the servo rate (5KHz), these steps comprise reading the sensors, executing the servo calculations, computing the servo output, and outputting this value to the servo

output channel. At the higher rate (15KHz), these steps comprise computing or looking-up the next trajectory value, executing the shaping method (if the correction for unwanted dynamics is not already included in the trajectory), and outputting the feedforward term to the feedforward output channel.

5 In the second example, there is only a single output path from the controlling computer chip to the hardware. An example of this is a disk drive in which a current is the output generated by the closed-loop servo and current is also used in the feedforward term. In order to actually implement this, the following steps are performed. At the servo rate (5KHz), these steps comprise
10 reading the sensors, executing the servo calculations, computing the servo output, and saving this value for use by the section below. At the higher rate (15KHz), these steps comprise computing or looking up the next trajectory value, executing the shaping method (if the correction for unwanted dynamics is not already included in the trajectory), and adding the feedforward term to the feedforward
15 term to the servo output computed above.

 There are many related configurations which either combine the above two approaches or are variations of these approaches. One such variation uses continuous or near continuous time outputs from the feedforward term. If the control hardware for a disk drive or any other machine is constructed so that
20 outputs can be scheduled in time, the feedforward outputs can run essentially asynchronously from the servo loop. In one such implementation, the voltages to the disk drive might be updated by a circuit at a high clock rate (e.g., 2 MHz). By loading a counter register with the time of the next voltage output, the hardware circuit can count down until the appropriate time and output the next voltage
25 value. This enables an optimized trajectory to be computed using any of the techniques herein (or by any other process), and to be output at a rate sufficiently high so that the system can be commanded to move in an optimized (or near optimized) fashion without effecting the servo rate.

 An additional variation on the approaches presented herein is to
30 use one of the shaped switched formulations so that only full scale voltages (or

any other parameter) are output. For example, it is possible to use unity magnitude ShapersTM to take a switching voltage command signal designed only for a rigid body system, and to modify the switching voltage command signal so that the switching voltage command signal moves the system with little vibration.

- 5 This approach enables the circuit to become a simple counter driven switch that changes its output at a preset time.

A further variation is to use an interrupt-driven approach in which times to output values are scheduled and an interrupt is generated (using state of the art computer techniques) at the appropriate time. At the time of the interrupt,
10 an appropriate output (or voltage switch) is provided by the controller chip or other device. Single or multiple hardware timers may be used to interrupt a DSP or microcontroller in the disk drive. Still another variation is to use a separate device, such as a programmable logic array, that is issued a single command which, in turn, generates a series of precisely-timed commands to the current
15 loop. The DSP or microcontroller can be programmed in an asynchronous control loop that maintains a list of switch times and required transitions.

8.0 PV Approach

A PV table comprises a trajectory curve which defines the velocity
20 of a system component, such as head 76, in terms of that component's position, i.e., the distance that the component has yet to go in order to reach its final position. To use a PV table, an actual position of the component is compared to its desired position. The difference between these two values is then used to look up a velocity in the PV table for the component. Many disk drive systems rely on
25 a PV table to determine their inputs. These inputs, however, can result in unwanted vibrations in the system. The techniques presented below can be used to reduce and/or limit such vibrations.

This aspect of the invention is a method of generating a trajectory for inclusion in a PV table which is used in controlling movement of a component
30 in a dynamic system. The method generates a trajectory in accordance with a

technique for reducing unwanted dynamics of the component, i.e., generating a good move. The trajectory is then stored in the PV table, and the component is controlled to move along the trajectory stored in the PV table.

In more detail, a good move is generated for the system using any of the techniques described in section 5 above. Specifically, the system is modeled, a “good” input is applied to the system, and the system’s reaction to the good input is stored in a PV table as a trajectory for the system. In this manner, good moves can be re-cast into a PV table for a system, thereby providing a way to reduce unwanted system dynamics while staying within a PV formulation. Taking this approach one step further, a series of good moves can be generated using this technique, and the series of good moves can be stored in a series of parameterized PV tables.

9.0 PV Feedback Approach

In prior art disk drive systems, the velocity determined from a PV table is merely fed forward into the system, as shown, for example, in the conventional disk drive system diagram depicted in Figure 13. This could lead to unwanted system vibrations. This aspect of the invention, however, shapes the velocity before it is provided to the system and, in addition, performs inverse shaping in the system’s feedback loop, thereby correcting the feedback so as not to co-opt the operation of the PV table.

Figure 14 shows an example of a system diagram for a disk drive that is controlled in accordance with this aspect of the invention. The disk drive includes PV table 84, shaper 86, and inverse shaper 87. Shaper 86 is placed in the feedforward loop following PV table 84 so as to shape the velocity output therefrom. Inverse shaper 87, which comprises the inverse of shaper 86, is placed in the feedback loop. The relationship between inverse shape 87 and shaper 86, in either the time domain or the frequency domain, is as follows:

$$\text{if shaper} = A/B, \text{ then shaper}^{-1} = B/A.$$

The combination of shaper 86 and inverse shaper 87 reduce unwanted system dynamics, such as vibrations of head 76. Specifically, shaper 86 alters the velocity input to the system so as to reduce vibrations in head 76 resulting from system movement, and inverse shaper 87 operates to restore loop stability to what it was prior to insertion of the shaper 86 in the forward loop. Shaper 86 and inverse shaper 87 are not limited to the Input ShapersTM and inverse Input ShapersTM described in U.S. Patents Nos. 4,916,635 and 5,638,635. In fact, shaper 86 and inverse shaper 87 can be any pole-zero dynamic block, IIR filter, FIR filter, tapped continuous delay line filter, or the like.

Figures 15 and 16 show relationships between inputs and outputs of a shaper ("IS") and inverse shaper ("IS⁻¹"), respectively, formed using an FIR filter, with A as the input. Specifically, relationships between the inputs and outputs of IS and IS⁻¹ are as follows:

$$y_n = \sum_{i=0}^N A_i x_{n-i}$$

$$x_n = \frac{y_n}{A_0} - \frac{1}{A_0} \sum_{i=1}^N A_i x_{n-i}$$

Figures 17 and 18, show relationships between inputs and outputs of a shaper and an inverse shaper ("IS⁻¹"), respectively, which are formed using a tapped continuous delay line filter. Specifically, relationships between inputs and outputs of IS and IS⁻¹ are as follows:

$$y(t) = A_0 x(t) + \sum_{i=1}^N A_i x(t - T_i)$$

$$x(t) = \frac{1}{A_0} y(t) - \frac{1}{A_0} \sum_{i=1}^N A_i x(t - T_i)$$

Figures 19 and 20, show relationships between inputs and outputs of a shaper ("IS") and an inverse shaper ("IS⁻¹"), respectively, which are formed using an IIR filter. Specifically, relationships between inputs and outputs of IS and IS⁻¹ are as follows:

$$y_n = \frac{1}{B_0} \sum_{i=1}^N A_i x_{n-i} - \frac{1}{B_0} \sum_{j=1}^M B_j y_{n-j}$$

$$x_n = \frac{1}{A_0} \sum_{j=0}^M B_j y_{n-j} - \frac{1}{A_0} \sum_{i=1}^N A_i x_{n-i}$$

5

To summarize, this aspect of the invention is directed to a method and corresponding apparatus for using a PV table to control a component, such as head 76, in a dynamic system, such as disk drive 10. The invention generates a position variable for the component and determines a velocity command for the component using the PV table, where the velocity command is determined based on the position variable. The velocity command is then shaped using an Input Shaper™ or the like in order to generate a shaped velocity command, whereafter the component is controlled to move based on the shaped velocity command. In the invention, a preset position of the component is compared to a measured position of the component in order to determine the position variable, and inverse shaping is performed on the measured position prior to comparing the measured position to the preset position.

20 10.0 N-Dimensional PV Table

The present invention also provides an enhanced PV table which may, or may not, be used in connection with the foregoing feedback approach and the foregoing techniques for generating good moves. As background, the same PV table may not produce accurate results for different distance moves, among other things. To address this problem, conventional disk drive systems typically

include one, two or maybe even three PV tables, i.e., one table for short moves, one table for medium-distance moves, and one table for long moves. Which table is selected depends upon the distance of the desired move. Since only three discrete values are provided for the movement distance, the system may not reach
5 its final destination as quickly as desired.

The present invention provides a better approach, namely to generate an N-dimensional ($N > 2$) PV table in which velocity is a function of position and a function of a third (fourth, fifth, etc.) variable, such as movement distance, resistance, temperature, etc. This approach effectively provides
10 increased movement speed, since the requested velocity values more closely represent physical limitations of the disk drive for substantially all movement distances. Moreover, this approach makes more sense than the conventional formulation, especially in the disk drive area, since disk drive systems are third order in nature and a conventional PV approach is second order in nature.
15 Although the present invention may use a PV table having any number N ($N > 2$) of dimensions, for the sake of simplicity, the examples provided herein refer usually to a three-dimensional PV table.

In order to determine trajectories for a PV table, a dynamic model of the system must be determined. An example of such a model is partial fraction
20 expansion equations 19. A system input, which is a function of time and which will move the model a desired distance, is then generated based on the model. For example, the system input may consist of a series of switch times and voltage levels, or a digital sequence of voltage levels. The input, in conjunction with the system model, is used to simulate the desired motion of the system. Any form of
25 the model that yields both a position and a velocity output is suitable. As an example, the third order voltage-to-position transfer function

$$H(s) = \frac{A}{s} * \frac{a}{s+a} * \frac{b}{s+b}$$

could be transformed and manipulated so that position and velocity are available as outputs. Using the commutative property of multiplication, the transfer function can be rearranged and then broken up to yield a "block diagram" with
5 voltage input and position and velocity outputs as follows:

$$\begin{aligned} \text{Voltage} &\rightarrow A \rightarrow \frac{a}{s+a} \rightarrow \frac{b}{s+b} \rightarrow \text{Velocity} \\ \text{Velocity} &\rightarrow \frac{1}{s} \rightarrow \text{Position} \end{aligned}$$

The above "block diagram" is then used as the basis of a computer simulation that yields the velocity and position outputs corresponding the voltage input. The integration is performed forward in time. If both the form of the input (e.g. three switch times and three voltage levels) and the model are simple, then
10 direct analytical solution of the system model to time domain equations can be used as an alternative approach to simulation. The velocity, and position outputs of the simulation are then tabulated to form one version of the PV table.

The present invention enables three approaches to PV table generation. First, a shaped input can be integrated forward to generate a PV table
15 -- in the above block diagram a shaper would be inserted following the voltage input. Second, an unshaped input can be integrated forward and an output of the integration can be shaped and stored in a table. Third, a vibration-reducing trajectory can be computed using a constraint-based approach, this input can be integrated forward, and the output thereof stored in a table. Prior to the derivation
20 of the partial fraction expansion equations shown above, there was no way to generate an input that was guaranteed to get the system to its final destination; therefore forward integration was not a viable approach. Reverse integration from a final condition was commonly used.

Using the generated input, system outputs are then determined over time so as to generate values of position as a function of time and velocity as a function of time. These values are then re-cast as velocity as a function of position. To generate a three-dimensional PV table, the above process is repeated
5 for the third variable in order to generate velocity as a function of both position and the third variable. The process may then be repeated for additional variables.

Since a three-dimensional PV table may require large amounts of memory space, and therefore may not be practical in all circumstances, the present invention provides several ways in which to approximate operation of a
10 three-dimensional PV table using a series of PV trajectories. For example, the invention generates a series of PV trajectories for various movement distances, stores these trajectories, and selects trajectories corresponding to a desired movement distance while ignoring all other trajectories. Thus, in this case, one of the series trajectories is selected from the position-velocity table based on the
15 desired movement distance and the system is controlled accordingly.

Another way to approximate a three-dimensional PV table is to perform curve fitting on a series trajectories in a PV table, such as those shown in the PV table of Figure 21. With regard to Figure 21, it is noted that, in the realm of computer disk drives, an actual target velocity is typically not included in the
20 PV table. Instead, a velocity command, comprising a target velocity plus an additional term relating to the actuator arm's effort to stay on track, is included in the PV table. With regard to curve fitting, since the curves shown in Figure 21 are substantially regular, it is possible to parameterize the curves and to generate a function which can be used to generate a single PV trajectory to control the
25 system.

Figure 22 shows examples of parameterized curves which were generated from the curves shown in Figure 21. For the example shown in Figure 22, an estimate of curves between the lowest (3000) and the highest (100) curve could be obtained by taking a weighted average of the lowest and highest curves
30 based on movement distance. Consequently, in this example, an entire series of

curves can be estimated by taking a weighted average of only two curves and using original movement distance to adjust the weights in the weighted average. Another way to approximate a three-dimensional PV table is to generate a custom PV table for each movement distance in real-time. This can be done using the system equations 19 for a computer disk drive set forth in section 4 above.

It is also possible to modify a series of trajectories in a PV table based on measurements of system parameter variations, such as variations in temperature, resistance, etc. This is done by estimating system parameters while motion is in progress, and determining whether the system parameters have varied from predetermined system parameters. Trajectories in the PV table are then modified based on any determined system parameter variations, whereafter the modified trajectories are stored in the PV table. Any method of estimating the system parameters may be used in connection with the present invention, including a conventional parameter estimator. For example, as a disk drive heats up, resistance therein changes. By looking at prior move responses, it is possible to estimate the resistance, to determine whether the resistance has changed, and to recalculate the drive's PV table, if necessary.

More specifically, in a disk drive system, during a first part of a move, the system is in saturation and, therefore, the PV table is inactive. This corresponds to issuing a step command in voltage to accelerate movement as rapidly as possible. During this acceleration phase, the actual current flowing through a voice coil motor used to convert electrical energy to mechanical energy can be measured. Knowing this, it is possible to perform an energy balance calculation to determine energy losses in the system due to resistance. The energy lost due to resistance equals the energy input to the disk drive minus kinetic energy of the voice coil motor minus energy stored in the voice coil inductor. This determination is made assuming that the inertia of the voice coil motor and the inductance of the voice coil are known or can be determined.

In real-time, the following steps are performed in order to estimate resistance: (i) for each time step, measure the actual current and the actual

voltage applied to the drive's voice coil motor, (ii) integrate power in the drive (determined by multiplying voltage by current) over time to determine the total energy input to the system, (iii) calculate the instantaneous kinetic energy of the voice coil motor, (iv) calculate the instantaneous energy in the motor inductance, 5 (v) calculate the integral of drive current squared over time, (vi) determine the estimated resistance by subtracting, from the energy input, the kinetic energy and the energy in the inductor divided by the integral of the current over time. Thus, after each integration, an estimated resistance for the disk drive is calculated. This can then be used to update the PV table.

10 Similar energy of momentum balance equations can be used to estimate other system parameters. For example, the following equation can be used to estimate motor torque:

$$K_t = \frac{J\Omega}{\int i dt}.$$

This equation can be solved in real-time, and can be solved over a whole move or 15 incrementally starting at any time during the move.

The foregoing techniques for generating PV tables can be calculated off-line, thereby making it possible to parameterize or curve-fit PV tables as a function of system parameters as well as movement distance. Consequently, it is then possible to retrieve a PV table based on movement 20 distance and system parameters. Moreover, it is noted that an N-dimensional PV table can be used outside of the context of the vibration reduction methods described herein, and that a non-dimensional PV table can be used in connection with all aspects of the present invention. A non-dimensional PV table comprises a PV table in which the independent variable on the X-axis of the PV table has 25 been scaled using a predetermined scaling factor. Such a factor may be, for example, a maximum number of tracks moved, or the like.

11.0 Shape on Transient ("SHOT")

Conventional implementations of the PV approach to controlling a disk drive encompass variations of the following steps: (i) ramping the current command to saturation (various techniques are used for this); (ii) commanding full, saturated current until some braking condition is satisfied, (iii) transitioning to full, saturated deceleration until the PV curve is crossed; (iv) following the PV curve until the drive is close to the final destination; and (v) turning on a terminal controller to bring the system on track. The preponderance of vibration, both mechanical and acoustic, is created by the sudden transitions at the beginning and middle of the PV move. Consequently, Input Shaping™ (or any other vibration-reducing technique) need be applied to only these portions of the trajectory.

A new sequence of operations, using SHOT, is as follows: (i) Input Shape™ the current command to saturation; (ii) command full, saturated current until some braking condition is satisfied; (iii) Input Shape™ the transition to full, saturated deceleration until the PV curve is crossed; (iv) follow the PV curve until the drive is close to its final destination; and (v) turn on a terminal controller to bring the system on track. Since the transitions to saturation are both just steps, the shaped transitions become shaped steps (or staircases).

Shaping can be rendered less effective if the input results in saturation and the command generator is unaware of the saturation. There are several methods for dealing with this situation. It is possible to command the system into saturation using estimates of when saturation should occur based on previous moves. For example, by estimating the maximum voltage and the coil resistance (or the quotient of maximum voltage/coil resistance) the maximum current in saturation can be obtained. Once the system is shaped into saturation, the saturation current can be calculated by measuring the acceleration and the velocity, since current is related to acceleration by a constant and the effective voltage is the saturation voltage minus the back EMF constant times the velocity.

1 Based on these calculations, it is possible to compute the actual saturation
2 level. It is then important to command only enough of an input to keep the system in
3 saturation and not exceed this level by too great of a value. If this value is exceeded by a
4 considerable amount, the shaping that is applied when the command is reversed to slow
5 the system down will be "chopped-off" at the beginning. For example, if an output
6 command of 5 volts from a DAC will saturate the current amplifier in steady state at the
7 current velocity, then a command of 6 volts would be undesirable. During the transition
8 to deceleration, if this error is left uncorrected, the shaper will reduce the voltage to, e.g.,
9 5.5 volts as the first part of the shaping process, yet the amplifier will remain saturated.
10 Therefore, the effect of shaping is degraded.

11 While the SHOT technique is well suited for adding to the PV approach, it
12 is by no means limited to PV. Any method of commanding a disk drive to move that
13 causes significant transitions in the command to the system is a candidate for SHOT. The
14 user need simply use shaped transitions instead of sudden or ramped transitions. The key
15 to this approach is that while sudden transitions cause vibrations and noise, and smooth
16 transitions often cause vibrations and noise (although less so than sudden transitions);
17 shaped transitions can be constructed to yield any level of vibrations and noise. This
18 makes the use of shaped transitions desirable because the effects are predictable and the
19 move is lengthened by the minimum amount. SHOT can also be used for transitions
20 caused by sudden gain changes as well as command changes. In this application, the gain
21 is altered in a shaped manner from one level to another using any one of the shaping
22 techniques described herein or from the literature.

23

24 12.0. Conclusion

25 At this point, it is reiterated that all aspects of the present invention can be
26 implemented in hardware, software or a combination of thereof. Moreover, although the
27 invention has been described in the context of computer disk drives, it may apply equally
28 to other types of data storage devices (of which a computer disk drive is one), including,
29 but not limited to, optical drives, tape drives, dual-actuated disk drives, and holographic

1 storage devices which read from, and write to, data storage media other than magnetic
2 disks.

3 The present invention has been described with respect to particular
4 illustrative embodiments. It is to be understood that the invention is not limited to the
5 above-described embodiments and modifications thereto, and that various changes and
6 modifications may be made by those of ordinary skill in the art without departing from
7 the spirit and scope of the appended claims.

8

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211